



User Manual for Designated Consumer

PATNET Portal

Version 2.2





Notice

© 2021 PositiveEdge Solutions Pvt. Ltd. All rights reserved.

The PositiveEdge name and logo are registered trademarks.

This is a controlled document. Unauthorized access, copying, replication or usage for a purpose other than for which it is intended, are prohibited.

All trademarks that appear in the document have been used for identification purposes only and belong to their respective companies.

Table of Contents

1.	About this Document.....	5
	Intended Audience	5
2.	New DC Registration Process.....	5
3.	Initial Login Process	11
4.	Forgot User ID?	14
5.	Forgot Password?	17
6.	Reset Login Details for a DC.....	19
7.	Resubmission of the Reversed DC Registration	24
8.	Intimation about DC Registration Approval	26
9.	DC Profile Update by the Plant Head	27
10.	Existing DC Registration Update Process.....	29
	10.1. Login to the New PATNET Portal.....	29
	10.2. Existing DC Profile Update.....	30
11.	E-Filing for a Designated Consumer	33
	11.1. Form 1 Filling by the Energy Manager	33
	11.2. Verification of Form 1 by the Plant Head	38
	11.3. Modify Form 1 Details by the Energy Manager	43
	11.4. Form A Filling by the Energy Manager	44
	11.5. Verification of Form A by the Plant Head.....	48
	11.6. Modify Form A Details by the Energy Manager	53
	11.7. Form 2 Filling by the Plant Head.....	54
	11.8. Initial Form 3 Filling by the Plant Head	58
	11.9. Final Form 3 Filling by the Plant Head	61
12.	Eligible Entity Registration Process	66
	12.1. Login to the New PATNET Portal.....	66
	12.2. Eligible Entity Registration and ESCerts Information.....	66
	12.3. New Eligible Entity Registration.....	69
	12.4. On-Hold Eligible Entity Registration	76
	12.5. Rejected Eligible Entity Registration.....	77
	12.6. Approved Eligible Entity Registration	78
	12.7. Partial ESCerts Introduction.....	78
13.	Trading Dashboard.....	80
	13.1. ESCerts ISSUED\ENTITLED TO BE PURCHASED	80



13.2.	Trading.....	80
13.3.	Banked/Extinguished ESCerts	82
14.	Submission of FORM D by Plant Head for Non-Eligibility Entity Registration.....	82
15.	Submission of FORM D by Plant Head for a DC who has participated in Eligibility Entity Registration Process.....	88

1. About this Document

The purpose of this document is to describe how **Designated Consumers (DC)** can use the PAT NET Portal.

Intended Audience


This document is intended for the following list of users.

- **Energy Manager/Energy Auditor – EM/EA**
- **Plant Head - PH**

2. New DC Registration Process

This section explains the registration process for a new Designated Consumers with the PAT NET Portal. Below given is the detailed steps to perform this operation.

1. Open e-filing portal by clicking the link (<https://escerts.gov.in>)
2. The 'LOGIN to BEE PATNET Portal' page appears. Click on **New User** button on the login page as shown in below image.



The screenshot shows the login page for the Bureau of Energy Efficiency (BEE) PATNET Portal. The page header includes the BEE logo and the text 'BUREAU OF ENERGY EFFICIENCY A statutory body under Ministry of Power, Government of India'. The main heading is 'LOGIN To BEE PATNET Portal'. There are three input fields: 'Enter UserId', 'Password', and 'Enter Captcha' (with the captcha 'g o h X 0'). Below the password field are links for 'Reset Details', 'Forgot UserId', and 'Forgot Password'. At the bottom, there are two buttons: 'LOGIN' and 'NEW USER'. To the right, a table displays the total number of Designated Consumers (DCs) by state.

State	Total DCs
Delhi	2
Gujarat	3
Jharkhand	2
Manipur	1

Figure 1: Login Page

3. The system redirects the user to select **User Type** page. Select **DC** from the User Type drop-down and then click on **Submit** button.




Figure 2: User Type Selection Page

4. The **Designated Consumer (DC) Registration Form** page appears as shown in below image.
 - a. Select **Sector and Sub-Sector**, to load all organization based on selected sectors and sub-sectors.
 - b. Select the **organization** from the list.
 - c. **Registration Number** will be populated automatically.
 - d. Fill all the required fields along with recovery email address and then click on **Next** button.





Figure 3: Designated Consumer – Registration Page

5. The **Energy Manager Details** section appears as shown in below image, perform the following action:
 - a. Enter the **Energy Manager/Energy Auditor Registration number**, and click on **find** button to auto populate the Energy Manager/Energy Auditor details.
 - b. Name of the energy manager field cannot be editable. Other details of the energy manger/energy auditor can be modified by the user if required.
 - c. Click on **Next** button after filling the Energy Manager/Energy Auditor details.



DESIGNATED CONSUMER (DC) REGISTRATION FORM
 Note: All fields marked with * are mandatory

Organisation **Energy Manager** Plant Head File Upload


EM Registration No. * EA0123156 Name * SHEKAR

Telephone No. with STD Code * 080 6777 Fax No. with STD Code 080 6785677

Mobile No. * +91 9897755567 Official Email Id * aman1323@gmail.com

Figure 4: Energy Manager Section – Registration Page

NOTE: Some of the sectors BEE restricted that an Energy Manager can work only for one DC at a time. In that case the below error message appears.



Organisation **Energy Manager** Plant Head File Upload

EM Registration No. * EM10031122 Name *


The energy manager is associated with another DC

Telephone No. with STD Code * Fax No. with STD Code

Mobile No. * +91 Official Email Id *

Figure 5: Error Message

- The **Plant Head Details** section appears enter all the mandatory details and then click on **Next** button.



DESIGNATED CONSUMER (DC) REGISTRATION FORM
Note : All fields marked with * are mandatory


Organisation Energy Manager **Plant Head** File Upload

Name * Darshan Planthead Telephone No. with STD Code * 080 33333333
 Fax No. with STD Code 080 44444444 Mobile No. * +91 9741192764
 Official Email Id * bgfr@gmail.com

Prev Cancel **Next**

Figure 6: Plant Head Section – Registration Page

- The **File Upload** section appears, under **Upload File** field select the file name from the drop-down to upload and click on the **Browse** button to browse the file from your system.



DESIGNATED CONSUMER (DC) REGISTRATION FORM
Note : All fields marked with * are mandatory

Organisation Energy Manager Plant Head **File Upload**

Upload Documents
 Upload File * PAN Browse

Prev Cancel **Submit**

Figure 7: File Upload Section – Registration Page

- All files except “Others” are mandatory to complete the registration process.

9. The browsed file will be added to the list under **Upload Documents** section as shown below. Click **Submit** button.

Upload Documents

Upload File*

Document Name	Document For	Format	Size	Action
IE1_PORTAL.JPG	TAN	JPG	57.36 KB	
IE2_MIGRATION.JPG	PAN	JPG	66.85 KB	
IE_notification.JPG	GSTIN	JPG	44.93 KB	
IE_notification.JPG	EPFO No	JPG	44.93 KB	
IE_notification.JPG	CIN	JPG	44.93 KB	
IE_notification.JPG	Reg. No. Under Shops and Establishment Act	JPG	44.93 KB	
IE_notification.JPG	EM Image	JPG	44.93 KB	
IE_notification.JPG	PH Image	JPG	44.93 KB	

Figure 8: Browsed Document List

10. The confirmation pop-up message appears, click on the **OK** button to proceed.

patnet.positiveedge.net:447 says

Are you sure want to proceed?

Figure 9: Proceed Message

NOTE: "Others" can be selected if DC need to upload any documents other than mentioned in the drop-down.

The DC **Successfully Registered** page appears as shown in below image.




Figure 10: Registration Success Page

NOTES:

- 1) **Mandatory fields to fill are marked with (*) mark.**
 - 2) **The DC Record will be assigned to 'Sector Project Engineer' and the owner details will be updated based on 'Sector Team'.**
12. After completion of registration, The Login credentials for both the **Energy Manager/Energy Auditor** and the **Plant Head** will be received in their registered email as shown below.




Figure 11: Registration Completion Email with Login Credentials

3. Initial Login Process

This section explain the first time log in process of DC.

1. Open e-filing portal by clicking the link (<https://escerts.gov.in>).
(The 'BEE PATNET portal Login' page appears).
2. Enter the **User ID** and **Password** which is received via email, enter the **Captcha** and then click on **Login** button as shown in below image.




Figure 12: Login Page

3. After successful login **Change Credentials** page will be displayed and user has to enter the new **User ID** and a new **Password**. **Confirm Password** and then click on **Submit** button as shown in below image.




Figure 13: Change Credentials Page

4. Success window appears as shown in below image. Click on **Login Again** button.




Figure 14: Password Change Success Page

5. Login page will be displayed again, enter the **new User Id** and **new Password**, enter the **Captcha** and then click on **Login** button.



Figure 15: Login Page

6. 'One Time Password' page will be displayed. User has to enter the **OTP** received on his/her registered mobile number and click on **Submit** button as shown in below image.




Figure 16: One Time Password Page

NOTE: If DC is not receiving the OTP in the registered mobile number then click on **Re-Send OTP** button to receive the new OTP.




Figure 17: Re-Send OTP

7. If the entered OTP is wrong an error message will show as shown below. Click on **Re-Send OTP** to receive a new OTP.




Figure 18: Re-send OTP

8. After entering the correct OTP, the DC will get logged in the portal.




Figure 19: Home Page

4. Forgot User ID?

This section explains the step by step procedure for **Designated Consumer** users (EM or PH) to reset their login user ID in case they forgot the user ID.

NOTE: *Forgot User ID feature can be used in case if the user remembers the registered email Id.*

Below given are the detailed steps to perform this operation from the PATNET portal.

1. Open e-filing portal by clicking the link (<https://escerts.gov.in>).
(The 'BEE PATNET portal Login' page appears).
2. Click on the **Forgot User ID** link which is present in the login page as shown in below image.




Figure 20: Forgot User ID

3. The system navigates to **Forgot User ID** window. Enter the **Email Id**, enter the **Captcha** then click the **Submit** button.




Figure 21: Forgot User ID Field

4. After successful submission, User ID will be sent to registered email ID of user and the system will show success message as shown in below image.




Figure 22: Forgot User ID Success Page




Figure 23: Email with User ID

NOTE: If the user enters wrong Email ID and clicks on Submit button then the system will show Invalid Email ID message as shown in below image.



Figure 24: Invalid Email Id Message


5. Forgot Password?

This section explains the step by step procedure for Designated Consumer users (EM or PH) to reset their login password.

NOTE: Forgot password feature can be used in case if the user remembers the login ID.

Below given are the detailed steps to perform this operation from the PATNET portal.

1. Open e-filing portal by clicking the link (<https://escerts.gov.in>).
(The 'BEE PATNET portal Login' page appears).
2. Click on the **Forgot Password** link which is present in the login page as shown in below image.



State	Total DCs
Karnataka	5
Maharashtra	2
Chhattisgarh	1
Jammu and Kashmir	1

Figure 25: Forgot Password

3. The **Forgot Password** window appears in the system. Enter the **User Id**, enter the **Captcha** displayed below the textbox and then click the **Submit** button.




Figure 26: Forgot Password Field

4. After successful changing a password, the system will send the new password to the registered email id and success message as shown in below image.




Figure 27: Forgot Password Success Page



Figure 28: Email with New Password

NOTE: If user enters wrong user ID, system will show Invalid User ID message as shown in below image.




Figure 29: Invalid User Id Message

6. Reset Login Details for a DC

This section explain the process of changing the details of the Plant head and the energy manager in their absence.

In some cases Plant head leaves organisation without handing over their existing user details. In these scenarios Designated Consumer can reset their details by using “**Reset User**” functionality available in PATNET Portal home page.

Designated Consumer can reset their login Id and password by following the below steps.

1. Open e-filing portal by clicking the link (<https://escerts.gov.in>).
(The ‘BEE PATNET portal Login’ page appears).
2. Click on **Reset Details** link which is present in the login page as shown in below image.




Figure 30: Reset Details

- The system will redirect the user to the **Reset Details** page, enter the recovery **Email Id** given by the DC at the time of registration, enter the **Captcha** displayed below the textbox and then click the **Submit** button.




Figure 31: Reset Details Page

- After successful submission, a web link will be send to recovery email Id of DC and success message will be displayed as shown in below image.




Figure 32: Reset Details Success Page

NOTE: If given Recovery Email ID is wrong system show Invalid Email ID message as shown in below image.



Reset Details

Recovery email is invalid (or) Registration is not approved

Enter your recovery email:

Enter Captcha

x a f 8 v

Submit

Figure 33: Invalid Email ID Message

5. The authorized person who handles the recovery email will receive the link to reset the details.




Figure 34: Reset Email Link

- Click on the **Reset Link**, a portal page opens with the options to select the organisation. Select the organisation from the list to modify the details and click the **Submit** button.



Figure 35: Multi Organization Selection List

- The organization information page appears, modify the required login details and then click on **Update** button to update the details.




Figure 36: Modify User Detail

8. The Confirmation message pop-ups, click **Ok**.




Figure 37: Confirmation pop-up Message

9. On clicking the Update button, record will be updated and user will get success page.




Figure 38: Reset User Detail Success Page

10. After successful update of login details, an email with new login credentials will be sent to the registered email address of **energy manager** and **plant head**.

NOTE: Reset Link expires once user updates the record using this link.

7. Resubmission of the Reversed DC Registration

This section explains the process of resubmission of reversed DC registration. In some cases BEE may reverse the registration application.

1. EM and PH will receive the **email notification** regarding reversal of registration with the reason for reverse the application.




Figure 39: Registration Reversed Email

2. Energy Manger / Plant head can log in to PAT NET portal by using their credentials (Refer to section 3 for the login steps).
3. Click on the **Profile** link. The DC profile page will be displayed with **Reverse** status.



Figure 40: Reversed Status

4. Click on **Edit Profile** as shown in the below image.




Figure 41: Edit Profile

5. Modify the details and click on the **Submit** button.

VISHAL PLANTHEAD 060 66666666 070 77777777 +91 9741192764

Official Email Id *

Uploaded Documents

Upload File * Select Document Type ▾

Document Name	Document For	Format	View	Delete
REGDIS0001SK_PAT(2)2015-2018_CIN_Image.JPG	CIN	JPG		
REGDIS0001SK_PAT(2)2015-2018_EPFO No_Image.JPG	EPFO No	JPG		
REGDIS0001SK_PAT(2)2015-2018_GSTIN_Image.JPG	GSTIN	JPG		
REGDIS0001SK_PAT(2)2015-2018_Others_Image.JPG	Others	JPG		
REGDIS0001SK_PAT(2)2015-2018_PAN_Image.JPG	PAN	JPG		
REGDIS0001SK_PAT(2)2015-2018_Reg. No. Under Shops and Establishment Act_Image.JPG	Reg. No. Under Shops and Establishment Act	JPG		
REGDIS0001SK_PAT(2)2015-2018_TAN_Image.JPG	TAN	JPG		


Figure 42: Modify the Email ID

6. The **Confirmation** pop-up message appears, click on **OK** button.



Figure 43: Configuration Pop-up Message

7. The Portal users details updates successfully and **Status** updates to **Pending Approval**.



MY PROFILE Pending Approval

Details updated successfully!

Organisation Details

Sector*	Sub Sector*	Organisation*
Buildings	Buildings	Vishal BUILDERS
DC Registration No*	Year of Establishment*	Recovery Email Id*
REGDIS0001SK	2019	vb7@gmail.com

Unit Address

Address Line1*	Address Line2	City/Town/Village*	District
maple12	maple2	sikkim	sikkim
State*	Pin code*	Telephone No. with STD Code*	Fax No. with STD Code
Sikkim	560078	010-11111111	020-22222222
PAN No.*	TAN*	GSTIN*	CIN*
BELPK2076J	TAN3333355	GSTIN4444444444	CIN5555555555555555
State of GST Registration*	EPFO No.	Registration No. under Shops and	

Figure 44: Details Update Successful Message

8. Intimation about DC Registration Approval

EM and PH will receive the **email notification** regarding **Approval** of registration form as shown in below image.




Figure 45: DC Approved Email

1. On receiving the approved mail, DC can login to BE PAT NET portal and can continue with the PAT activities.




Figure 46: DC Profile with 'Approved' Status

9. DC Profile Update by the Plant Head

This section explain how the Plant Head updates the DC profile details.

1. Log in to PATNET portal by using his/her login credentials (Refer to section 3 for the login steps).
2. On successful login the Plant Head home page appears as shown in below image. User has to click on **Profile** link.




Figure 47: Home Page

3. The DC profile page will be displayed with **Edit Profile** button as shown in below image.

NOTE: 'Edit Profile' button is enable only for a Plant Head to edit the information.




Figure 48: DC Record with 'Edit Profile' Button for PH

4. Click on **Edit Profile** button, and click on **Change Person** button on 'Energy Manager Details' section as shown in below image.





Figure 49: DC Profile in Editable Format


- Once user click on **Change Person** button, the Energy Manager's fields is editable. User has to enter new **EM/EA registration number** and click find button, to populate the energy manager details.



The screenshot shows the 'Energy Manager Details' form. The 'EM Registration No.' field is highlighted with a red box. Other fields include Name, Telephone No. with STD Code, Fax No. with STD Code, Mobile No., and Official Email Id. A 'Cancel' button is visible at the top right.

Figure 50: Enter New EM Registration No.

- Click on **Change Image** button to Upload EM profile image.



The screenshot shows the 'Energy Manager Details' form with the 'Change Person' button highlighted. The 'Change Image' button is highlighted with a red box. The form contains the following data: Name: Sudhakar I.E, EM Registration No.: EA144144, Telephone No.: 080 6778, Fax No.: 080 6785678, Mobile No.: +91 9897755567, and Official Email Id: aman144@gmail.com.

Figure 51: Change Image

- Click on submit button to update the details. **Success message** will be displayed on successful updated of energy manager.
- Plant Head** himself can update the details. Otherwise by using **Reset Details** functionality DC can update both EM and PH details.

10. Existing DC Registration Update Process

DCs who already using old PAT Net portal can use the same login details in the new platform. This section explains the process for update their existing registration details.

10.1.Login to the New PATNET Portal

- Open e-filing portal by clicking the link (<https://escerts.gov.in>). (The BEE PATNET Portal Login page appears).
- Plant Head / Energy Manger Logins to the BEE PATNET Portal with his/her existing **User Id** and **Password** (Refer to section 3 for the login steps).

10.2.Existing DC Profile Update

Old PAT NET portal registered DC need to update the missing details in the new system. This can be done by an Energy Manager / Plant Head. In the absence of Energy Manager Plant Head can update the details.

1. DC user log in to the BEE PATNET Portal with his/her existing **User Id** and **Password** (Refer to section 3 for the login steps).
2. On successful login the **Notification Alert** message pop-ups, click **Proceed**.




Figure 52: Notification Alert Message

3. The DC profile Page appears, Click **Edit Profile** to edit and update the Details.





Figure 53: Click Edit Profile

4. Enter the missing organization Information.

Unit Address			
Address Line1 *	Address Line2	City/Town/Village *	District
<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>
<small>The Address Line1 field is required.</small>		<small>The City/Town/Village field is required.</small>	
State *	Pin code *	Telephone No. with STD Code *	Fax No. with STD Code
<input type="text" value="Andhra Pradesh"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>
	<small>The Pin code field is required.</small>	<small>The STD Code field is required. The Telephone number field is required</small>	
PAN No. *	TAN *	GSTIN *	CIN *
<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>
<small>The PAN No. field is required.</small>	<small>The TAN field is required.</small>	<small>The GSTIN field is required.</small>	<small>The CIN field is required.</small>
State of GST Registration *	EPFO No.	Registration No. under Shops and Establishment Act	
<input type="text" value="Select State of Registration"/>	<input type="text"/>	<input type="text"/>	
<small>The State of GST Registration field is required.</small>			

Figure 54: DC Information Field

NOTE: If the EM is not mapped to the DC, then the EM information fields appear blank as shown in below image.



Energy Manager Details


Name * EM Registration No. * Telephone No. with STD Code * Fax No. with STD Code

Mobile No. * Official Email Id *

+91-

Figure 55: Energy Manager Information Fields showing blank

5. Click **Change Person** to update the EM details.



Energy Manager Details **Change Person**


Name * EM Registration No. * Telephone No. with STD Code * Fax No. with STD Code

Mobile No. * Official Email Id *

+91-

Figure 56: Click Change Person

6. Enter the **EM Registration Number** and click **find** button, then all other information of EM fields auto updates.



Energy Manager Details **Cancel**


EM Registration No. * Name * Telephone No. with STD Code * Fax No. with STD Code

Mobile No. * Official Email Id *


+91-

Figure 57: Enter EM Registration Number

7. Click on **Change Image** button to Upload EM profile image.



Energy Manager Details **Change Person**

 **Change Image**

Name * EM Registration No. * Telephone No. with STD Code * Fax No. with STD Code


Sudhakar I.E EA144144 080 6778 080 6785678

Mobile No. * Official Email Id *

+91 9897755567 aman144@gmail.com

Figure 58: Change Image

- If the mandatory information of PH is missing, update the details, Upload the documents and then click the **Submit** button (refer to section 2 step (Z) for the steps to upload documents).



Plant Head Details

Name * The Name field is required.

Telephone No. with STD Code * The STD Code field is required. The Telephone number field is required.

Fax No. with STD Code

Mobile No. * +91 The Mobile No. field is required.

Official Email Id * The Official Email Id field is required.

Uploaded Documents

Upload File *


Select Document Type

- Select Document Type
- PAN
- TAN
- GSTIN
- CIN
- EPFO No
- Reg. No. Under Shops and Establishment Act
- Others

Document Name Document For Format View Delete

Figure 59: Upload Documents

- The status of the DC record updates as **Approved** on the successful upload of all the documents and the DC can continue with PAT activates.



BUREAU OF ENERGY EFFICIENCY
A statutory body under Ministry of Power, Government of India

HOME MY DASHBOARD Welcome JAYESH K SHAH

MY PROFILE Approved ✓

Figure 60: Status Updates as Approved

11. E-Filing for a Designated Consumer

11.1. Form 1 Filing by the Energy Manager

1. Click the link (<https://escerts.gov.in>).
(The 'BEE PATNET Portal' login page appears).
2. Refer to section 3 for the login steps.
3. On the successful login The 'BEE Energy Manager Home' page appears as shown in below image.




Figure 61: BEE Energy Manager Home Page

4. On the Home page click **My Dashboard** button on the top left of the page.




Figure 62: Click My Dashboard

5. The list of 'My Dashboard' functions popups, click **Dashboard** function from the list of dashboard functions.




Figure 63: Click Dashboard Function

6. The 'DC Dashboard – PAT Cycles' page appears.
7. PAT Cycle which DC is currently participating will be highlighted as shown below.
8. Click on the PAT Cycle image to open that PAT Cycle Dashboard.




Figure 64: Click Running PAT Cycle

9. Click **M&V** Status icon and under **Form 1** for respective financial year click **Submit** link to enter the Form 1 details.




Figure 65: Click Submit

10. The 'DC Details Information' page for the selected financial year appears as shown in below image.





Figure 66: DC Details Information Page

11. Verify the DC details information and click **Next** button.
12. The page navigates to 'Production Details' page as shown in below image.




Product	Product Name	Unit	Previous Year	Current Year
Product 1	Caustic Soda	tonne		11.00
Product 2	Chlorine	tonne		12.00
Product 3	Soda Ash	tonne		13.00
Total Equivalent Product Produced		tonne		36.00

Figure 67: Form-1 - Production Details Page

Perform following actions on the 'Production Details' page:

- Enter the **Product Name** and other details as required.
- Click **Add Row** button to include more products in the list.
- Click **Delete** icon to remove a product from the list.
- Click **Prev** button to navigate back to the 'DC details information' page.
- Click **Next** button to navigate to the 'Energy Consumption' details page.

13. On Click Next the page navigates to 'Energy Consumption' details page as shown in below image.




Item	Unit	Previous Year	Current Year
a) Energy Consumption Details			
1) Total Electricity Purchased from Grid/Other Source *	Million kWh		40.00
2) Total Electricity Generated *	Million kWh		50.00
3) Total Electricity Exported *	Million kWh		60.00
4) Total Electrical Energy Consumption *	Million kWh		70.00
5) Total Solid Fuel Consumption *	Million kcal		80.45
6) Total Liquid Fuel Consumption *	Million kcal		90.56
7) Total Gaseous Fuel Consumption *	Million kcal		95.00

Figure 68: Form-1- Energy Consumption Details Page

Perform following actions on the 'Energy Consumption Details' page:

- Enter the **Current Year** 'Energy Consumption Details.
- If the previous year data exists, then the user can view the previous data.
- Click **Next** button to navigate to the 'Sector Wise Details' page.

14. The page navigates to the 'Sector – Wise Details' page, upload the Pro-forma file and check the declaration and click on submit to submit the Form 1.



FORM-1
Financial Year- 2015-16

Sector - Wise Details



Pulp and Paper Pulp and Paper Sf

Note 1: All sectors specific pro-forma, details of which are given above, are available on the Bureau of Energy Efficiency official website.

Upload Pro-Forma

Upload File * Select Proforma

Uploaded Documents


Document Name	Document For	Format	Sizes	Actions
REGPINP0030PB_a7b7617f-94d0-e911-80e0-00155d5e9403_BEE DE.xlsx	Proforma	XLSX	9750	 

I/We undertake that the information supplied in the Form 1 and pro-forma is accurate to the best of my knowledge and the data furnished in the Form 1 has been adhered to the data given in the concerned pro-forma.

Cancel Prev **Submit**

Figure 69: Form-1 - Sector – Wise Details page

15. The Confirmation pop-up message appears, click **OK** button to continue with the submission.



patnet.positiveedge.net:447 says

Are you sure want to proceed?

OK Cancel

Figure 70: Confirmation Pop-up Message

16. On submitting the Form 1, the **Print** button enables.




Figure 71: Form-1- Print Button

17. Click the **Print** button to take print out of Form 1.

18. The print format of the Form 1 is as shown in the below image.

<h2 style="margin: 0;">Form1</h2> <p style="margin: 0;">[See rule3]</p>																							
<p>Details of information regarding total energy consumed and specific energy consumption per unit of production.</p>																							
<table border="1" style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th colspan="3" style="text-align: left; padding: 5px;">Section-A (General Information Details)</th> </tr> <tr> <th style="width: 5%; padding: 5px;">S.No</th> <th style="width: 45%; padding: 5px;">General Details</th> <th style="width: 50%; padding: 5px;">Description</th> </tr> </thead> <tbody> <tr> <td style="text-align: center; padding: 5px;">1</td> <td style="padding: 5px;">Name of the Unit</td> <td style="padding: 5px;">Sree Rayalseema Alkalies & Allied Chemical Limited, Gondiparla, Kurnool</td> </tr> <tr> <td style="text-align: center; padding: 5px;">2</td> <td style="padding: 5px;">i) Year of Establishment</td> <td style="padding: 5px;">2012</td> </tr> <tr> <td style="text-align: center; padding: 5px;"></td> <td style="padding: 5px;">ii) Registration Number (As provided by BEE)</td> <td style="padding: 5px;">REGCNA0019AP</td> </tr> <tr> <td style="text-align: center; padding: 5px;">3</td> <td style="padding: 5px;">Sector and Sub-Sector in which designated Consumer falls</td> <td style="padding: 5px;">Sector : Chlor Alkali Sub Sector : Chlor-Alkali</td> </tr> <tr> <td style="text-align: center; padding: 5px;">4</td> <td style="padding: 5px;">i) Complete Address of DCs Unit Location (including Chief Executive's name & designation) with Mobile, Telephone, Fax No & Email</td> <td style="padding: 5px;">Shiv Designation : Plant Head Email : garimas@positiveedge.net Mobile : 8750723137 TelePhone : 91-67788777 Fax : 08-88782742 Address : Gondiparla, City : Kurnool State : PinCode : 135001</td> </tr> </tbody> </table>			Section-A (General Information Details)			S.No	General Details	Description	1	Name of the Unit	Sree Rayalseema Alkalies & Allied Chemical Limited, Gondiparla, Kurnool	2	i) Year of Establishment	2012		ii) Registration Number (As provided by BEE)	REGCNA0019AP	3	Sector and Sub-Sector in which designated Consumer falls	Sector : Chlor Alkali Sub Sector : Chlor-Alkali	4	i) Complete Address of DCs Unit Location (including Chief Executive's name & designation) with Mobile, Telephone, Fax No & Email	Shiv Designation : Plant Head Email : garimas@positiveedge.net Mobile : 8750723137 TelePhone : 91-67788777 Fax : 08-88782742 Address : Gondiparla, City : Kurnool State : PinCode : 135001
Section-A (General Information Details)																							
S.No	General Details	Description																					
1	Name of the Unit	Sree Rayalseema Alkalies & Allied Chemical Limited, Gondiparla, Kurnool																					
2	i) Year of Establishment	2012																					
	ii) Registration Number (As provided by BEE)	REGCNA0019AP																					
3	Sector and Sub-Sector in which designated Consumer falls	Sector : Chlor Alkali Sub Sector : Chlor-Alkali																					
4	i) Complete Address of DCs Unit Location (including Chief Executive's name & designation) with Mobile, Telephone, Fax No & Email	Shiv Designation : Plant Head Email : garimas@positiveedge.net Mobile : 8750723137 TelePhone : 91-67788777 Fax : 08-88782742 Address : Gondiparla, City : Kurnool State : PinCode : 135001																					

Figure 72: Form-1- Print Preview

11.2.Verification of Form 1 by the Plant Head

On successful submission of Form 1 by the Energy Manager the Plant Head will receive an email notification regarding the submission of the Form 1.

This section explains the process of verification of Form 1.

1. Click the link (<https://escerts.gov.in>) .
2. (The 'BEE PATNET Portal' login page appears).
2. Refer to section 3 for the login steps.

On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears and is shown below.




Figure 73: Plant Head Home Page

3. Click **My Dashboard** next to Home icon on the top left of the DC Home page.




Figure 74: Click My Dashboard

4. The list of 'MY Dashboard' functions popups, click **Dashboard** function from the list of My Dashboard functions.




Figure 75: Click Dashboard Function

5. The 'DC Dashboard – PAT Cycles' page appears.
6. PAT Cycle which DC is currently participating will be highlighted as shown below.
7. Click on the PAT Cycle image to open that PAT Cycle Dashboard.




Figure 76: Click Running PAT Cycle

8. The 'Designated Consumer Dashboard' page appears, click **M&V Status** icon and under **Form 1** for respective financial year click **View** button to view the Form 1 details.




Figure 77: Click View

9. The 'DC Details Information' page for the selected financial year appears as shown in below image.





Figure 78: Form-1- DC Details Information Page

10. Verify the DC details page information and click **Next** button.
11. The page navigates to 'Production Details' page as shown in below image.



FORM-1
Financial Year- 2012-13

Details of Information regarding Total Energy Consumed and Specific Energy Consumption per unit of Production

Production Details

Energy Consumption Details Of Manufacturing Industries Specified As Designated Consumers

Sector - Wise Details

Manufacturing Industries Notified as Designated Consumers

Product	Product Name	Unit	Previous Year	Current Year
Product 1	Caustic Soda	tonne		11.00
Product 2	Chlorine	tonne		12.00
Product 3	Soda Ash	tonne		13.00
Total Equivalent Product Produced		tonne		36.00


Prev Cancel Next

Figure 79: Form-1 - Production Details Page

Perform following actions on the 'Production Details' page:

- Click the **Previous** button to navigate back to the 'DC Details Information' page.
- Click the **Next** button to navigate to the 'Energy Consumption Details' page.

12. The page navigates to 'Energy Consumption Details' page as shown in below image.



FORM-1
Financial Year- 2012-13

Details of Information regarding Total Energy Consumed and Specific Energy Consumption per unit of Production

Production Details

Energy Consumption Details Of Manufacturing Industries Specified As Designated Consumers

Sector - Wise Details

Energy Consumption Details Of Manufacturing Industries Specified As Designated Consumers
Note: All fields are marked with * are mandatory

Item	Unit	Previous Year	Current Year
a) Energy Consumption Details			
1) Total Electricity Purchased from Grid/Other Source *	Million kWh		40.000
2) Total Electricity Generated *	Million kWh		50.000
3) Total Electricity Exported *	Million kWh		60.000
4) Total Electrical Energy Consumption *	Million kWh		70.000
5) Total Solid Fuel Consumption *	Million kcal		80.450
6) Total Liquid Fuel Consumption *	Million kcal		90.560
7) Total Gaseous Fuel Consumption *	Million kcal		95.000


Prev Cancel Next

Figure 80: Form-1- Energy Consumption Details Page

Perform following action on the 'Energy Consumption Details' page:

- Click the **Previous** button to navigate back to the 'Production Details' page.
- Click the **Next** button to navigate to the 'Sector Wise' details page.

13. The page navigates to 'Sector wise Details' page as shown in below image.



FORM-1
Financial Year- 2015-16

Sector - Wise Details



Pulp and Paper Pulp and Paper Sf

Note 1: All sectors specific pro-forma, details of which are given above, are available on the Bureau of Energy Efficiency official website.

Upload Pro-Forma

Upload File* Select Proforma

Uploaded Documents

Document Name	Document For	Format	Sizes	Actions
REGPNP0030PB_b944b7dc-8bd4-e911-80e0-00155d5e9403_BEE DE.xlsx	Proforma	XLSX	9750	 


I/We undertake that the information supplied in the Form 1 and pro-forma is accurate to the best of my knowledge and the data furnished in the Form 1 has been adhered to the data given in the concerned pro-forma.

Cancel **Prev** **Print** **Submit** **Reverse**

Figure 81: Form-1 - Sector - Wise Details Page

Perform following action on the 'Sector Wise Details' page:

- PH will review the Form 1 details entered by the EM and click the **Submit** button.
- The Confirmation pop-up message appears, click **OK** button to submit Form 1 to the PH for verification.




patnet.positiveedge.net:447 says

Are you sure want to proceed?

OK **Cancel**

Figure 82: Confirmation Pop-up Message

14. On submit of Form 1, the print button enables. Click the **Print** button to take a printout of Form 1 PDF pages.



FORM-1
Financial Year- 2019-20

Details of Information regarding Total Energy Consumed and Specific Energy Consumption per unit of Production

Production Details

Energy Consumption Details Of Manufacturing Industries Specified As Designated Consumers

Sector - Wise Details

Sector - Wise Details

Name of The Sector	Sub-Sector	Pro-forma in which the details to be furnished
Cement	Cement	Sb

Note 1: All sector specific pro-forma, details of which are given above, are available on the Bureau of Energy Efficiency official website.

I/We undertake that the information supplied in the Form 1 and pro-forma is accurate to the best of my knowledge and the data furnished in the Form 1 has been adhered to the data given in the concerned pro-forma.

Buttons: Cancel, Prev, **Print**

Figure 83: Form-1 - Print Button

15. The print format of the Form 1 will be as shown in the below image.

Form 1		
[See rule3]		
Details of information regarding total energy consumed and specific energy consumption per unit of production.		
Section-A (General Information Details)		
S.No	General Details	Description
1	Name of the Unit	SRIVARI CEMENT
2	i) Year of Establishment	2019
	ii) Registration Number (As provided by BEE)	SRIVARI CEMENT 179
3	Sector and Sub-Sector in which designated Consumer falls	Sector : Cement Sub Sector : Cement
4	i) Complete Address of DCs Unit Location (including Chief Executive's name & designation) with Mobile,Telephone,Fax No & Email	shov planthead Designation : Plant Head Email : bdew@gmail.com Mobile : 9741192764 TelePhone : 080-33333333 Fax : Address : maple1,maple2 City : marnalli State : bangalore PinCode : 560078
	ii) Registered Office Address	Address : maple1,maple2 City : marnalli State : bangalore PinCode : 560078

Figure 84: Form 1 Print Preview

- If PH is not satisfied with the Form 1 details entered by the EM, click the **Reverse** button to send back Form 1 for the EM to modify.
- The confirmation pop-up message appears, click **OK** button to reverse Form 1 to the Energy Manager.




Figure 85: Confirmation Message

11.3.Modify Form 1 Details by the Energy Manager

If the Form 1 reversed by PH, EM will receive email notification. EM can log in and can update the Form 1 and can resubmit again for PH verification.

1. Click the link (<https://escerts.gov.in>).
(The 'BEE PATNET Portal' login page appears).
2. Refer to section 3 for the login steps.
3. Modify the Form 1 details and click on the **Update** button on the 'Sector Wise Details' page. (Refer to section 11.1 4 for navigation).




Figure 86: Click Update

NOTES:

- 1) **Once Form 1 (1st year) is submitted, EM will be eligible to fill the 2nd year Form 1 as mentioned above. Once the Second year submits then EM can start with 3rd year Form 1.**
- 2) **Same process will be followed for all the three year Form 1.**


11.4. Form A Filling by the Energy Manager

On submission of 3rd year Form 1 EM can fill the Form A details as explained below.

1. Click the link (<https://escerts.gov.in>)
(The 'BEE PATNET Portal' login page appears).
2. Refer to section 3 for the login steps.

Perform the following actions on the Designated Consumer Dashboard page (Refer to section 11.1 4 for navigation).

3. Click **M&V Status** icon and under **Form A** click **Submit** link to enter the Form A details.



FTZ0019AP - NFCL Kakinada - II, Kakinada East Godavari, Andhra Pradesh
PAT Cycle:2015-18


M & V Status Escerts Issuance Check Verification Trading Compliance Escerts Banked

FORM 1 2015-16 2016-17 2017-18 **FORM A** FORM B FORM 2 FORM 3 First Second Attachments

View | View | View | **Submit** View Submit Submit Submit

Figure 87: Click Submit

4. The 'Performance Assessment Document' details page appears as shown in below image.



FORM-A Performance Assessment Document Guidelines

Performance Assessment Document


General Details	Description
Name of the Designated Consumer	SRIVARI CEMENT
Registration Number	SRIVARI CEMENT 179
Sector	Cement
Sub Sector	Cement
Accredited Energy Auditor	
Empanelled Accredited Energy Auditor	AARTHI INTERNATIONAL
Registration Number	AEA012345

Cancel **Next**

Figure 88: Performance Assessment Document Page

5. View the DC details information and click **Next** button.

- The page navigates to 'List of Document Submitted' page which displays all the three Form 1 submission dates.




The screenshot shows the 'List of Document Submitted' page. On the left is a sidebar with 'FORM-A' and navigation options: 'Performance Assessment Document', 'List of Document Submit' (highlighted), 'Specific Energy Consumption', and 'Energy Efficiency Project Implemented During Current Cycle'. The main content area has a table with columns 'Document', 'Financial Year', and 'Submission Date'. Below the table are 'Prev', 'Cancel', and 'Next' buttons.

Document	Financial Year	Submission Date
Baseline Data		dd/mm/yyyy
Form 1	2012-13	10-05-2019
Form 1	2013-14	10-05-2019
Form 1	2014-15	10-05-2019
Form 2		dd/mm/yyyy
Form 3		dd/mm/yyyy

Figure 89: List of Documents Submitted page

Perform following actions on the 'Documents Submit' details page:

- Click the **Previous** button to navigate back to the 'Performance Assessment Document' details page.
 - Click the **Next** button to navigate to the 'Specific Energy Consumption' details page.
- The 'Specific Energy Consumption' page appears as shown in below image.



The screenshot shows the 'Specific Energy Consumption' page. The sidebar has 'Specific Energy Consumption' highlighted. The main content area has a table with columns 'Specific Energy Consumption', 'Value', and 'Unit'. A note states: 'Note: All fields are marked with * are mandatory'. Below the table are 'Prev', 'Cancel', and 'Next' buttons.


Specific Energy Consumption	Value	Unit
a) Specific Energy Consumption		
1) Specific Energy Consumption (Baseline) as Notified *	29.000	Toe/Tonne
2) Production (Baseline) as Notified *	14.000	Tonne
3) Target specific energy consumption SEC as Notified *	18.000	Toe/Tonne
4) Difference of Baseline SEC & Target SEC as Notified *	11.000	Toe/Tonne
5) Normalized Specific Energy Consumption Achieved *	12.000	Toe/Tonne
6) Energy Saving Certificates *	84.000	No's

Figure 90: Specific Energy Consumption Page


Enter the following values in the 'Specific Energy Consumption' details page.

- Enter the **Specific Energy Consumption** (Baseline) as Notified value.
- Enter the **Production** (Baseline) as Notified value.

- Enter the **Target SEC** as Notified value.
- The **Difference of Baseline SEC & Target SEC as Notified value**, the application auto calculates the value as follows:



- Enter the **Normalized Specific Energy Consumption Achieved** value.
- The **Energy Saving Certificates** value, the application auto calculates the value as follows:



- Enter the values and click **Prev** button to navigate back to the 'Specific Energy Consumption' details page.
 - Enter the values and click **Next** button to navigate to the 'Energy efficiency Project' details page.
8. The 'Energy Efficiency Project Implemented' details page appears as shown in below image.

Project	Year Of Implementation	Annual Energy Savings in Lakh kWh	Annual Energy Saving in toe*	Annual Energy Consumption (before) in Toe	Annual Energy Consumption (after) in Toe	Energy Cost (Rs. per Kwh/te)	Investment (Rs. in crores)
Proje	2018	10	20	30	50	10	4
Proje	2017	20	30	40	60	15	4.5
Proje	2015	30	50	60	70	20	5
Proje	2014	45	70	80	90	25	3
Proje	2013	55	80	90	100	30	2

Figure 91: Energy Efficiency Project Implemented

- Enter the **Project Name** and other related details.
 - Click **Add Row** button to include more projects in the list.
 - Click **Delete** icon to remove a project from the list.
 - Click **Prev** button to navigate back to the 'Specific Energy Consumption' details page.
 - Select the **Declaration Checkbox** to validate the project information entered.
 - Click on **Submit** button to submit the Form A.
9. The Confirmation pop-up message appears, click **OK** button to continue with the submission.





Figure 92: Confirmation Pop-up Message

10. On submitting the Form A, the **Print** button enables.



FORM-A

Energy Efficiency Project Implemented During Current Cycle

Project	Year Of Implementation	Annual Energy Savings in Lakh kWh	Annual Energy Saving in toe*	Annual Energy Consumption (before) in Toe	Annual Energy Consumption (after) in Toe	Energy Cost (Rs. per Kwh/tie)	Investment (Rs. in crores)
project 1	2018	12.00	13.00	14.00	15.00	16.00	18.00

* Please indicate the weighted average Gross Calorific Value (GCV) of coal considered for calculation of toe:..... kcal/kg

Declaration

I/We undertake that the information supplied in this Performance Assessment Document is accurate to the best of my knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/We agree to extend necessary assistance in case of any enquiry to be made in the matter.

Prev Cancel Print

Figure 93: Print Button

11. Click the **Print** button to get the print out of Form A.

12. The print format of the Form A is as shown in the below image.

FORM A		
[(See Rule 6.1)]		
PERFORMANCE ASSESSMENT DOCUMENT		
(To be filled by Designated Consumer)		
1.	Name of designated consumer	SRIVARI CEMENT
2.	Registration Number	SRIVARI CEMENT 179
3.	Sector	Cement
4.	Sub-Sector	Cement
5.	Accredited Energy Auditor	
a	Empanelled Accredited Energy auditor Firm name	AARTHI INTERNATIONAL
b	Registration number of Firm	AEA012345
6.	List of documents submitted (Attach a copy self attested by Energy Manager and counter signed by Accredited Energy Auditor)	
	Baseline Data	Submission Status
	Submission Date	
	Form 1 - 2019-20_SRVARI CEMENT 179 (2019-20)	PH Submitted to SPE
		09/09/2019
	Form 1 - 2020-21_SRVARI CEMENT 179 (2020-21)	PH Submitted to SPE
		10/09/2019
	Form 1 - 2021-22_SRVARI CEMENT 179	PH Submitted to SPE
		10/09/2019

Figure 94: Form A Print Preview

11.5.Verification of Form A by the Plant Head

On successful submission of FORM A the PH will receive and email notification to verify the details submitted by the EM.

1. Click the link (<https://escerts.gov.in>)
(The 'BEE PATNET Portal' login page appears).
2. Refer to section **3** for the login steps.

- On Successful login to the BEE PATNET portal with Plant Head user name and password, the Plant Head Home page appears as shown below.




Figure 95: Plant Head Home Page

Perform the following actions on the Designated Consumer Dashboard page to **Submit/Reverse** Form A. (Refer to section 11.2 (3) for navigating to the Designated Consumer Home page).

- Click the **M&V** Status icon and for the DC Registration Number under **Form A** click **View** button to view and Submit or Reverse Form A.




Figure 96: DC Dashboard Page

5. The 'Performance Assessment Document' details page appears as shown in below image.




Figure 97: Performance Assessment Document Page

Perform the following action:

- Select the **EmAEA organization** from the 'Empanelled Accredited Energy Auditor' drop-down.
- On the selection of EmAEA organisation from the drop-down, the **Registration Number** of selected EmAEA organisation auto populates.
- Click the **Next** button to navigate to the 'List of Document' page.

6. The 'List of Document Submitted' details page appears as shown in below image.





Figure 98: List of Document Submit Page

Perform the following action:

- Click the **Prev** button to navigate to the ‘Performance Assessment Document’ details page.
- Click the **Next** button to navigate to the ‘Specific Energy Consumption’ details page.

7. The ‘Specific Energy Consumption’ details page appears as shown in below image.




Specific Energy Consumption	Value	Unit
a) Specific Energy Consumption		
1) Specific Energy Consumption (Baseline) as Notified *	129.000	Toe/Tonne
2) Production (Baseline) as Notified *	10.000	Tonne
3) Target specific energy consumption SEC as Notified *	112.000	Toe/Tonne
4) Difference of Baseline SEC & Target SEC as Notified *	17.000	Toe/Tonne
5) Normalized Specific Energy Consumption Achieved *	50.000	Toe/Tonne
6) Energy Saving Certificates *	620.000	No's

Figure 99: Specific Energy Consumption Page

Perform the following action:

- Click the **Prev** button to navigate back to the ‘List of Document Submitted’ details page.
- Click the **Next** button to navigate to the ‘Energy Efficiency Project’ details page.

8. The ‘Energy Efficiency Project Implemented during Current Cycle’ page appears as shown in below image.



Project	Year Of Implementation	Annual Energy Savings in Lakh kWh	Annual Energy Saving in toe*	Annual Energy Consumption (before) in Toe	Annual Energy Consumption (after) in Toe	Energy Cost (Rs. per kWh/Toe)	Investment (Rs. in crores)
PROJECT 1	201	123.00	124.00	125.00	126.00	127.00	128.00

* Please indicate the weighted average Gross Calorific Value (GCV) of coal considered for calculation of toe:..... kcal/kg

Declaration

I/We undertake that the information supplied in this Performance Assessment Document is accurate to the best of my knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/We agree to extend necessary assistance in case of any enquiry to be made in the matter.

Figure 100: Energy Efficiency Project Page

Performs the following action:

- PH will review the Form A project details and click the **Submit** button after select the Declaration check box.
- Then confirmation pop-up message appears, click **OK** button to continue with the Form A submission.




Figure 101: Confirmation Pop-up Message

9. Click the **Print** button to take a printout of Form A PDF pages. The format of the Form A will be as shown in the below image.
10. The format of the Form A will be as shown in the below image.

FORM A [(See Rule 6.1)] PERFORMANCE ASSESSMENT DOCUMENT (To be filled by Designated Consumer)		
1.	Name of designated consumer	Alumn Company Ltd
2.	Registration Number	REG100AL
3.	Sector	Aluminium
4.	Sub-Sector	Cold Rolling Sheet
5.	Accredited Energy Auditor	
	Empanelled Accredited Energy auditor	Mahesh m
	Registration Number	HREGA22354NA
6.	List of documents submitted (Attach a copy self attested by Energy Manager and counter signed by Accredited Energy Auditor)	
	Document	Submission Status
		Submission Date
6.1.	Form 1 - 2015-16_REG100AL(2015-16) Specify the year in bracket	19/04/2019
6.2.	Form 1 - 2015-16_REG100AL(2015-16) Specify the year in bracket	18/04/2019

Figure 102: Form-A Print Preview

NOTE: On Updating of Form A by the PH an email notification will be sent to the 'SDA-Technical Officer (TO)' to Verify/Review the Form A.

11. If PH is not satisfied with the Form A details entered by the EM, click the **Reverse** button to send back to the EM to update Form A details.
12. The confirmation pop-up message appears, click **OK** button.





Figure 103: Confirmation Message

11.6. Modify Form A Details by the Energy Manager

If a PH reverses Form A, then an EM receive an email notification, then EM has to re-login and update the Form A details.

1. Click the link (<https://escerts.gov.in>)
(The 'BEE PATNET Portal' login page appears).
2. Refer to section 3 for the login steps.
3. Modify the Form A details and click **Update** button on the 'Energy Efficiency Project' page.
(Refer to section 11.1 4 for navigation).



FORM-A

Energy Efficiency Project Implemented During Current Cycle Guidelines

Project	Year Of Implementation	Annual Energy Savings in Lakh kWh	Annual Energy Saving in toe*	Annual Energy Consumption (before) in Toe	Annual Energy Consumption (after) in Toe	Energy Cost (Rs. per Kwh/te)	Investment (Rs. in crores)
Project 1	2018	12.00	13.00	14.00	15.00	16.00	17.00

Add Row

* Please indicate the weighted average Gross Calorific Value (GCV) of coal considered for calculation of toe:..... kcal/kg

Declaration

I/We undertake that the information supplied in this Performance Assessment Document is accurate to the best of my knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/We agree to extend necessary assistance in case of any enquiry to be made in the matter.

Prev Cancel Print **Update**

Figure 104: Energy Efficiency Project Page

NOTE: Already completed PAT Cycle details can be viewed by DC from the dashboard. Completed PAT Cycle will be greyed out and the running pat cycle is highlighted as shown below.




Figure 105: Completed PAT Cycle and Running PAT Cycle

11.7. Form 2 Filling by the Plant Head

On successful submission of Form 1 by the Energy Manager for the first financial year the Plant Head can fill the Form 2.

This section explains the process of Form 2 Filling.

1. Click the link (<https://escerts.gov.in>)
2. (The 'BEE PATNET Portal' login page appears).
2. Refer to section 3 for the login steps.
3. On the successful login The 'BEE Plant Head Home' page appears as shown in below image.




Figure 106: BEE Energy Manager Home Page

4. On the Home page click **My Dashboard** button on the top left of the page.




Figure 107: Click My Dashboard

- The list of 'My Dashboard' functions popups, click **Dashboard** function from the list of dashboard functions.




Figure 108: Click Dashboard Function

- The 'DC Dashboard – PAT Cycles' page appears.
- PAT Cycle which DC is currently participating will be highlighted as shown below.
- Click on the PAT Cycle image to open that PAT Cycle Dashboard.




Figure 109: Click Running PAT Cycle

- Click **M&V Status** icon and under **Form 2** for respective financial year click **Submit** link to enter the Form 2 details.





Figure 110: Click Submit

10. The 'Details of Energy Saving' page appears as shown in below image.



FORM-2
 Details of energy saving measures recommended in the energy audit report(year)

S.No	Energy Saving Measures	Investment (Million Rs)	Reason for Not implementing the measure	Date of completion of measure/likely completion	Life Cycle Years	Oil	Gas	Coal	Electricity	Others	Delete
1											

Add Row


Cancel Submit

Figure 111: Production Details Page

Perform following actions on the 'Details of Energy Saving' page:

- Enter the **Energy Saving Measures** and other details as required.
- Click **Add Row** button to include more **Energy Saving Measures** in the list.
- Click **Delete** icon to remove a line item from the list.
- Click **Submit** button.

11. The Confirmation pop-up message appears, click **OK** button to continue with the submission.



patnet.positiveedge.net:447 says
 Are you sure want to proceed?

OK Cancel

Figure 112: Confirmation Pop-up Message

12. On submitting the Form 2, the **Print** button enables.

FORM-2
Form has been submitted successfully.
Details of energy saving measures recommended in the energy audit report(year)

S.No	Energy Saving Measures	Investment (Million Rs)	Reason for Not implementing the measure	Date of completion of measure/likely completion	Life Cycle Years	Annual energy Savings				
						Oil	Gas	Coal	Electricity	Others
1	test1	12.00	12	11-09-2019	12	12	13	14	15	16

Figure 113: Print Button Enables

13. Click the **Print** button to take print out of Form 2.

14. The print format of the Form 2 is as shown in the below image.

FORM 2
Details of energy saving measures recommended in the energy audit report(year)
[Refer Regulation 5(2)]

S.No	Energy Saving Measures(Suggested categories of areas of improvement and modification for obtaining details of energy savings - See annexure 3)	Investment (Million Rs)	Reason for not implementing the measure	Date of completion of measure/likely to completion	Life Cycle Years	Annual Energy Savings				
						Oil	Gas	Coal	Electricity	Other
(1)	(2)	(3)	(4)	(5)	(6)	(7)	(8)	(9)	(10)	(11)
1	test1	12.00	12	11-09-2019	12	12	13	14	15	16

Signature _____
Signature Abison I.E

Figure 114: Print Preview

NOTE: On the verification of Form 2 an email notification will be sent to the SDA-Technical Officer (TO) to Review/Verify Form 2.

11.8. Initial Form 3 Filling by the Plant Head

On successful submission of Form 2 Plant Head logs in and fills the initial Form 3 as per the Mandatory Audit feedback.

This section explains the process of submission of Form 3.

1. Click the link (<https://escerts.gov.in>).
(The 'BEE PATNET Portal' login page appears).
2. Refer to section 3 for the login steps.
3. On the successful login The 'BEE Energy Plant Head Home' page appears as shown in below image.




Figure 115: BEE Energy Manager Home Page

4. On the Home page click **My Dashboard** button on the top left of the page.




Figure 116: Click My Dashboard

5. The list of 'My Dashboard' functions popups, click **Dashboard** function from the list of dashboard functions.




Figure 117: Click Dashboard Function

6. The 'DC Dashboard – PAT Cycles' page appears.
7. PAT Cycle which DC is currently participating will be highlighted as shown below.
8. Click on the PAT Cycle image to open that PAT Cycle Dashboard.




Figure 118: Click Running PAT Cycle

9. Click **M&V Status** icon and under **Form 3** for the first year click **Submit** link to enter the Form 3 details.




Figure 119: Click Submit

10. The 'Details of Energy Conservation' page appears as shown in below image.

FORM-3
 Details of energy conservation measures implemented, investment made and savings in energy achieved and progress made in implementation of other recommendations.

A. Implemented

S.No	Description of energy efficiency improvement measure	Category	Investment (Rupees)	Verified savings (Rupees)	Verified energy savings	Units	Fuel	Remarks	Delete
1	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="button" value="Delete"/>

B. Under Implementation

S.No	Description of energy efficiency improvement measure	Category	Investment (Rupees) estimated	Verified savings (Rupees) estimated	Verified energy savings estimated	Units	Fuel	Status of Implementation	Delete
1	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="button" value="Delete"/>

Figure 120: Production Details Page

Perform following actions on the 'Details of Energy Conservation' page:

- Enter the **Energy Saving Measures Implemented** and other details as required.
- Click **Add Row** button to include more **Energy Saving Measures Implemented** in the list.
- Click **Delete** icon to remove a line item from the list.
- Enter the **Energy Saving Measures under Implementation** and other details as required.
- Click **Add Row** button to include more **Energy Saving Measures under Implementation** in the list.
- Click **Delete** icon to remove a line item from the list.
- Click **Submit** button.

11. The Confirmation pop-up message appears, click **OK** button to continue with the submission.




Figure 121: Confirmation Pop-up Message

12. On submitting the Form 3, the **Print** button enables.

FORM-3
Form has been submitted successfully!

Details of energy conservation measures implemented, investment made and savings in energy achieved and progress made in implementation of other recommendations.

A. Implemented

S.No	Description of energy efficiency improvement measure	Category	Investment (Rupees)	Verified savings (Rupees)	Verified energy savings	Units	Fuel	Remarks
1	test1	cement	12.0000	13.0000	14	15	16	testd

B. Under Implementation

S.No	Description of energy efficiency improvement measure	Category	Investment (Rupees) estimated	Verified savings (Rupees) estimated	Verified energy savings estimated	Units	Fuel	Status of Implementation
1	test2	cemnt	14.0000	15.0000	161	18	19	testd

Figure 122: Print Button Enables

13. Click the **Print** button to take print out of Form 3.

14. The print format of the Form 3 is as shown in the below image.

FORM 3								
[Refer Regulation 5(3)]								
DETAILS OF ENERGY CONSERVATION MEASURES IMPLEMENTED, INVESTMENT MADE AND SAVINGS IN ENERGY ACHIEVED AND PROGRESS MADE IN THE IMPLEMENTATION OF OTHER RECOMMENDATIONS								
A. Implemented:								
Sl. No	Description of energy efficiency improvement measure	Category	Investment(Rupees)	Verified Savings(Rupees)	Verified Energy Savings	Units	Fuel	Remarks
1	test1	cement	12.00	13.00	14.00	15	16	testd
B. Under Implementation:								
Sl. No	Description of energy efficiency improvement measure	Category	Investment(Rupees) estimated	Verified Savings(Rupees) estimated	Verified Energy Savings estimated	Units	Fuel	Status of Implementation
1	test2	cemnt	14.00	15.00	161.00	18	19	testd
Signature SUDHAKAR Bharathi CEMENT SHAKKEER PLANTHEAD erdf@gmail.com 080-66000000 080-77777777 maple1maple2 mamallibangalore 560078						Signature Abison I.E AEAG078 Seal		

Figure 123: Form-3- Print Preview

NOTE: On verification of Form 3 an email notification will be sent to the SDA-Technical Officer (TO) to Review/Verify Form 3.

11.9.Final Form 3 Filling by the Plant Head

On successful submission of initial Form 3 Plant Head logs in and fills the Final Form 3 before the end of PAT Cycle.

This section explains the process of submission of final Form 3.

1. Click the link (<https://escerts.gov.in>).
(The 'BEE PATNET Portal' login page appears).
2. Refer to section **3** for the login steps.

3. On the successful login The 'BEE Energy Plant Head Home' page appears as shown in below image.




Figure 124: BEE Energy Manager Home Page

4. On the Home page click **My Dashboard** button on the top left of the page.




Figure 125: Click My Dashboard

5. The list of 'My Dashboard' functions popups, click **Dashboard** function from the list of dashboard functions.




Figure 126: Click Dashboard Function

6. The 'DC Dashboard – PAT Cycles' page appears.
7. PAT Cycle which DC is currently participating will be highlighted as shown below.
8. Click on the PAT Cycle image to open that PAT Cycle Dashboard.




Figure 127: Click Running PAT Cycle

9. Click **M&V Status** icon and under **Form 3** for the second year click **Submit** link to enter the Form 3 details.




Figure 128: Click Submit

10. The 'Details of Energy Conservation' page appears as shown in below image.

FORM-3
 Details of energy conservation measures implemented, investment made and savings in energy achieved and progress made in implementation of other recommendations.

A. Implemented

S.No	Description of energy efficiency improvement measure	Category	Investment (Rupees)	Verified savings (Rupees)	Verified energy savings	Units	Fuel	Remarks	Delete
1	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="button" value="Delete"/>

B. Under Implementation

S.No	Description of energy efficiency improvement measure	Category	Investment (Rupees) estimated	Verified savings (Rupees) estimated	Verified energy savings estimated	Units	Fuel	Status of Implementation	Delete
1	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="button" value="Delete"/>

Figure 129: Production Details Page

Perform following actions on the 'Details of Energy Conservation' page:

- Enter the **Energy Saving Measures Implemented** and other details as required.
- Click **Add Row** button to include more **Energy Saving Measures Implemented** in the list.
- Click **Delete** icon to remove a line item from the list.
- Enter the **Energy Saving Measures under Implementation** and other details as required.
- Click **Add Row** button to include more **Energy Saving Measures under Implementation** in the list.
- Click **Delete** icon to remove a line item from the list.
- Click **Submit** button.

11. The Confirmation pop-up message appears, click **OK** button to continue with the submission.

patnet.positiveedge.net:447 says
 Are you sure want to proceed?

Figure 130: Confirmation Pop-up Message

12. On submitting the Form 3, the **Print** button enables.

FORM-3
Form has been submitted successfully!

Details of energy conservation measures implemented, investment made and savings in energy achieved and progress made in implementation of other recommendations.

A. Implemented

S.No	Description of energy efficiency improvement measure	Category	Investment (Rupees)	Verified savings (Rupees)	Verified energy savings	Units	Fuel	Remarks
1	test1	cement	12.0000	13.0000	14	15	16	testd

B. Under Implementation

S.No	Description of energy efficiency improvement measure	Category	Investment (Rupees) estimated	Verified savings (Rupees) estimated	Verified energy savings estimated	Units	Fuel	Status of Implementation
1	test2	cemnt	14.0000	15.0000	161	18	19	testd

Figure 131: Print Button Enables

13. Click the **Print** button to take print out of Form 3.

14. The print format of the Form 3 is as shown in the below image.

FORM 3
[Refer Regulation 5(3)]
DETAILS OF ENERGY CONSERVATION MEASURES IMPLEMENTED, INVESTMENT MADE AND SAVINGS IN ENERGY ACHIEVED AND PROGRESS MADE IN THE IMPLEMENTATION OF OTHER RECOMMENDATIONS

A. Implemented:

Sl. No	Description of energy efficiency improvement measure	Category	Investment (Rupees)	Verified Savings (Rupees)	Verified Energy Savings	Units	Fuel	Remarks
1	test1	cement	12.00	13.00	14.00	15	16	testd

B. Under Implementation:

Sl. No	Description of energy efficiency improvement measure	Category	Investment (Rupees) estimated	Verified Savings (Rupees) estimated	Verified Energy Savings estimated	Units	Fuel	Status of Implementation
1	test2	cemnt	14.00	15.00	161.00	18	19	testd

Signature
SUDHAKAR
Bharathi CEMENT
SHAKKEER PLANTHEAD
erdf@gmail.com
080-00000000
080-77777777
maple1maple2 mamallibangalore 560078

Signature
Abison I.E
AEA0078
Seal

Figure 132: Form-3 -Print Preview

NOTE: On the verification of Form 3 an email notification will be sent to the SDA-Technical Officer (TO) to Review/Verify Form 3.

12. Eligible Entity Registration Process

12.1. Login to the New PATNET Portal

1. Open e-filing portal by clicking the link (<https://escerts.gov.in>).
(The BEE PATNET Portal Login page appears).
2. Plant Head Logins to the BEE PATNET Portal with his/her existing **User Id** and **Password**
(Refer to section 3 for the login steps).
3. On the successful login The 'Home' page appears as shown in below image.




Figure 13333: BEE Energy Manager Home Page

12.2. Eligible Entity Registration and ESCerts Information

1. On the Home page click **My Dashboard** button on the top left of the page.




Figure 134: Click My Dashboard

2. The list of 'My Dashboard' functions popups, click **Dashboard** function from the list of dashboard functions.




Figure 135: Click Dashboard Function

3. The 'DC Dashboard – PAT Cycles' page appears.
4. PAT Cycle which DC is currently participating will be highlighted as shown below.
5. Click on the PAT Cycle image to open that PAT Cycle Dashboard.




Figure 136: Click Running PAT Cycle

6. Click on **ESCerts Issuance** tab to view the ESCerts related and Eligible entity related information as shown below.
 - a. No.Of ESCerts(Claimed) is the number of ESCerts claimed by DC as per the M&V
 - b. No.Of ESCerts (Approved by MOP) is the final number of ESCerts approved by MoP
 - c. Serial No.Of Issued ESCerts: This will be the serial number of the issued ESCerts.
 - d. Eligibility Type : Eligibility type of the DC for the PAT Cycle
 - e. Blocked ESCerts: Number of ESCerts Blocked to meet the compliance from the banked ESCerts in case the DC is a Buyer.
 - f. Banked ESCerts: Number of ESCerts Banked from the previous cycle.




Figure 137: Click ESCerts Issuance

7. Eligible Entity Registration section will have different link based on the registration status
 - a. **Submit** : In case if the DC is Registering as fresh eligible entity then the link will be "Submit"

PAT Cycle: PAT(1)2012-2015

PAT Forms
 ESCCerts Issuance
 Check Verification
 Trading
 Compliance
 ESCCerts Banked

No.Of ESCCerts(Claimed)	No.Of ESCCerts(Approved by MOP)	Serial No.Of Issued ESCCerts	Eligibility Type	Blocked ESCCerts	Banked ESCCerts
14600	14600	01-05714666- CMT340031KA-171120 to 01-05729265- CMT340031KA-171120	NA	0	0

Eligible Entity Registration	
Form	Status
Submit	

Figure 138 : Fresh Eligible Entity-Submit

- b. **Participate In Trade:** In case DC already registered as an Eligible Entity and need to trade only the paid banked ESCCerts then the option will be Participate in Trade. The same link will be available if the DC is an eligible entity already and need to buy the ESCCerts (Buyer) in that particular PAT Cycle.

No.Of ESCCerts(Claimed)	No.Of ESCCerts(Approved by MOP)	Serial No.Of Issued ESCCerts	Eligibility Type	Blocked ESCCerts	Banked ESCCerts
17800	17800	NA	NA	0	0

Eligible Entity Registration	
Form	Status
Edit Info	Participate in Trade

Partial Participation Details			Download			
Form	Status	Certificate	Invoice	Advance Receipt	Refund Voucher	

Cancel

Figure 139: Participate in-Trade

- c. **Submit Transaction:** In case DC already registered as an Eligible Entity and need to trade the un-paid banked ESCCerts (Both Banked / New ESCCerts) then the option will be Participate in Trade.

PAT Forms
 ESCCerts Issuance
 Check Verification
 Trading
 Compliance
 ESCCerts Banked

No.Of ESCCerts(Claimed)	No.Of ESCCerts(Approved by MOP)	Serial No.Of Issued ESCCerts	Eligibility Type	Blocked ESCCerts	Banked ESCCerts
23400	23400	02-00041933- CMT340031KA-171120 to 02-00065332- CMT340031KA-171120	NA	0	0


Eligible Entity Registration	
Form	Status
Edit Info	Submit Transaction Details

Figure 140: Submit Transaction

12.3. New Eligible Entity Registration

DCs who are coming for the first time to register as an eligible entity can click on the Submit button available in the dash board as explained in the above section. New Eligible Entity Application contains mainly 4 sections as explained below


1. **Section A- PAT Cycle Details:** This is section contains the details of the PAT Cycle and DC information as shown below. User no need to fill any information in this section all information are read only here. Click on Next button to move to the next section.



General Details	Description
PAT Cycle	PAT(2)/2016-2019
DC Registration Number	CMT02002KA
DC Name	Orient Cement Jalgaon KARNATAKA
Sector	Cement
State	Karnataka
Name of State Designated Agency	Karnataka Renewable Energy Development Limited (KREDL)
Plant Address *	maple1, maple2, maple 3, bangalore, Karnataka, 560002
Plant Head Name	Sofia

Figure 141: EE Registration - Section A- PAT Cycle Details

2. **Section B – Owner Details:** In this section DC needs to fill the details of primary and secondary contact details of the DC also needs to fill the details of the mandatory document which is required for the Eligible Entity registration as per the Registry. Click on Next button to move to the next section.



Manufacturing industries Notified as Designated Consumers
Note: All fields are marked with * are mandatory

Primary Contact Name (Name of the Authorised Signatory) *

Designation *

Phone No. (with STD Code) *

Fax *

Mobile No *

E-mail Address *

Permanent Account Number(PAN) *


Tax Deduction and Collection Account Number(TAN) *

EPFO-Employees Provided Fund Organisation Registration No

Figure 142: EE Registration - Section B- Owner Details

3. **Section C – Payment Break-Up Info** : This section contains two sections as explained below

- a. **ESCerts Info:** This section explain the details of the information about the ESCerts as shown below.
 - i. **No. Of ESCerts Issued:** Number of ESCerts issued in that PAT Cycle if DC is a seller. For Buyer it will be 0
 - ii. **Banked ESCerts :** Total number of ESCerts carried from the previous cycle
 - iii. **Paid Banked ESCerts:** ESCerts fee paid ESCerts from the Banked ESCerts.
 - iv. **Un-Paid Banked ESCerts:** ESCerts fee not paid ESCerts from the Banked ESCerts.
 - v. **Available ESCerts:** Number of ESCerts available to introduce for trading.
 - vi. **ESCerts Introduced:** Total Number of ESCerts introduced for Trading.
 - vii. **Opening Balance:** Number of ESCerts available in the trading account.
 - viii. **Total Sold :** Number of ESCerts Sold by that particular DC



General Details	Description
No of ESCerts Issued	18532
Banked ESCerts	9032
Paid Banked ESCerts	3000
Un-paid Banked ESCerts	6032
Available ESCerts	24564
ESCerts Introduced	0
Opening Balance	0
Total Sold	0

Figure 143: EE Registration - Section C- Payment Break-Up Info

- b. **Registration Info:** This section explains the fees details of the Introducing ESCerts as shown below.
 - i. **One Time Registration Fee:** This fees is applicable only for the new DC who are registering for the first time. Its system calculated field.
 - ii. **ESCerts to be introduced for Trading:** The number of ESCerts which DC want to introduce for Trading.
 - iii. **ESCerts Fee:** Total value for the ESCerts. Its system calculated field.
 - iv. **Total Fee Basic Value:** This is the sum of registration fee and ESCerts Fee. Its system calculated field
 - v. **TDS deducted by DC (%):** DC can enter the TDS deducted (Proof for the same to be uploaded at the final submission)
 - vi. **POSOCO’s TDS share (50%):** Share for POSOCO after applying the TDS. Its system calculated field

- vii. **BEE's TDS Share (50%)** : Share for BEE after applying the TDS. Its system calculated field
- viii. **Total TDS deducted by DC** : Total TDS deducted from the DC. Its system calculated field
- ix. **Central GST (9.00%)** : Its system calculated field will be decided based on the DC's state.
- x. **State GST (9.00%)** : Its system calculated field will be decided based on the DC's state
- xi. **Integrated GST (18.00%)**: Its system calculated field will be decided based on the DC's state
- xii. **Total amount payable by DC**: The final amount to be paid by DC. Its system calculated field.
- xiii. **POSOCO's share**: Share of POSOCO from the total amount. Its system calculated field.
- xiv. **BEE's share**: Share of BEE from the total amount. Its system calculated field.

General Details	Description
One Time Registration Fee	15000
ESCerts to be introduced for Trading	24564
ESCerts Fee	122820
Total Fee: Basic Value	137820
TDS deducted by DC (%)	0
POSOCO's TDS share (50%)	0
BEE's TDS share (50%)	0
Total TDS deducted by DC	0

Figure 144: EE Registration – Calculation

Central GST (9.00%)	0
State GST (9.00%)	0
Integrated GST (18.00%)	24807.6
Total amount payable by DC	162627.6
POSOCO's share	68910.0
BEE's share	68910.0

Prev
Cancel
Next

Figure 145: EE Registration – Calculation

- Section D – Upload Files & Declaration:** The mandatory documents required to complete the Eligible Entity Registration should be uploaded here. All mandatory document will be list out in the Upload File drop down list. Select the document from the list and click on Browse button to upload the document.

REGISTRATION FORM
Eligible Entity Registration Form

- Section A - PAT Cycle Details
- Section B - Owner Details
- Section C - Payment Break-Up Info
- Section D - Uploaded Files & Declaration

Uploaded Files & Declaration

Upload Documents

Upload File * PAN Browse

Section D: Declaration

I/We certify that all information furnished above is/are true to the best of my/our knowledge and belief. I/We shall abide by such terms and conditions that the Central Electricity Regulatory Commission may impose from time to time, to participate in the ESCerts Exchange Mechanism from time to time.

INDEMNIFICATION
The Designated Consumer shall keep each of the Registry indemnified at all times and shall undertake to indemnify, defend and save the Registry harmless from any and all damages, losses, claims and actions, including those relating to injury to or death of any person or damage to property, demands, suits, recoveries, costs and expenses, court costs, attorney fees, and all other obligations by or to third parties, arising out of or resulting from the Registration/Exchange of ESCerts under ESCerts Exchange Mechanism. The Designated Consumer shall keep Registry indemnified at all times and shall undertake to indemnify, defend and save the Registry harmless from any and all damages, losses, claims and actions, arising out of disputes with Administrator, SDAs, as well as with Power Exchange(s), inclusive of confidentiality issues.

Prev
Cancel
Submit and Pay

Figure 146: EE Registration – Section D- Uploaded Files and Declaration

After uploading all documents accept the declaration by selecting the check box and click on **Submit and Pay** button to submit the Eligible Entity Registration. On successful registration user will receive the success message as shown below.

HOME MY DASHBOARD Welcome PARMESH

REGISTRATION FORM

Eligible Entity Registration Form

Registration Completed Successfully!

Registration Form For Designated Consumer to become Eligible Entity

Sector	Fertilizer
State	Karnataka
Name of State Designated Agency	Karnataka Renewable Energy Development Limited (KREDL)
Plant Address *	61/C, Chikkakallasandra, , Village, Subramanyapura, Bengaluru,, Karnataka, Karnataka, 560061
Plant Head Name	PARMESH
Plant Head Contact Details	9741192764
Number of ESCerts Issued	700
Postal Address *	61/C, Chikkakallasandra, , Village, Subramanyapura, Bengaluru,, Karnataka, Karnataka, 560061

- Section A - PAT Cycle Details
- Section B - Owner Details
- Section C - Payment Break-Up Info
- Section D - Uploaded Files & Declaration

Figure 147: EE Registration – Application Submission

After successful registration there will be button available to submit the payment details by clicking **Submit Transaction** as shown below.

Sector	Fertilizer
State	Karnataka
Name of State Designated Agency	Karnataka Renewable Energy Development Limited (KREDL)
Plant Address *	61/C, Chikkakallasandra, , Village, Subramanyapura, Bengaluru,, Karnataka, Karnataka, 560061
Plant Head Name	PARMESH
Plant Head Contact Details	9741192764
Number of ESCerts Issued	700
Postal Address *	61/C, Chikkakallasandra, , Village, Subramanyapura, Bengaluru,, Karnataka, Karnataka, 560061
Year of Establishment	2020

- Section A - PAT Cycle Details
- Section B - Owner Details
- Section C - Payment Break-Up Info
- Section D - Uploaded Files & Declaration

Figure 148: EE Registration – Submit Transaction

On click of Submit Transaction user will re direct to the payment details page as shown below. Fill all mandatory field in this page and click on Submit button after check on the self-declaration check box.

FTZ0078623KA - AGRO INDUSTRIES KARNATAKA
PAT Cycle: PAT(2)2016-2019

No.Of ESCerts(Claimed)	No.Of ESCerts(Approved by MOP)	Serial No.Of Issued ESCerts	Eligibility Type	Blocked ESCerts	Banked ESCerts
700	700	02-00177044-FTZ0078623KA-201020 to 02-00177743-FTZ0078623KA-201020	NA	0	0

Eligible Entity Registration	
Form	Status
Submit	Draft

Partial Participation Details		Download			
Form	Status	Certificate	Invoice	Advance Receipt	Refund Voucher
View	Draft				

Figure 151: EE Registration –Application Status

On the successful registration of Eligible Entity Registration the application will be submitted to Registry for further verification and approval. DC can download the Advance Receipt for the Payment they made as shown below

Eligible Entity Registration	
Form	Status
Edit Info	Submit Transaction Details Draft

Partial Participation Details		Download			
Form	Status	Certificate	Invoice	Advance Receipt	Refund Voucher
View	Draft				

Figure 152: EE Registration –Transaction Details

Before approving the Eligible Entity Registration Registry verifier will verify the payment submitted by the DC. Once the payment is verified then DC can download the Invoice for the same as shown below. Even the payment is verified the Eligible Entity Registration status remain as Draft. But the payment status will show as verified.

Eligible Entity Registration	
Form	Status
Edit Info	Submit Transaction Details Draft

Partial Participation Details		Download			
Form	Status	Certificate	Invoice	Advance Receipt	Refund Voucher
View	Verified				

Figure 153: EE Registration –Application Verification by Registry

12.4. On-Hold Eligible Entity Registration

On the successful registration of Eligible Entity Registration the application will be submitted to Registry for further verification and approval.

Some of the cases Registry may require some additional information required to process to application. In this scansion will keep those application in On-Hold with their comments. Once registry kept the application On-Hold DC can see the status as On-Hold in PAT Net portal as shown below. Also DC can see the reason for keeping the application On-Hold.




Figure 154: EE Registration –Application On-Hold by Registry

Click on the comment box to view the comment button to view the comments given by the Registry as shown below.




Figure 155: EE Registration –Comments on the application by Registry

In this case DC needs to update the application by uploading the necessary documents as per the comments provide by the Registry. DC has to give the comment at the time of uploading the documents. And finally click on Update button to submit back to Registry.




Figure 156: EE Registration –Application Resubmission

12.5.Rejected Eligible Entity Registration

On the successful registration of Eligible Entity Registration the application will be submitted to Registry for further verification and approval.

Some of the cases Registry may reject the application with their comments. Once registry Reject the application DC can see the status as Reject in PAT Net portal as shown below. Also DC can see the reason for keeping the application got Reject.




Figure 157: EE Registration –Application Rejected by Registry

Once the application Reject DC will get provision to request for the Refund for the money paid for the ESCerts. DC has to fill the bank details to get the refund. Click on Submit Bank Details to submit the bank details. Fill all required details and click on Submit button. Once the refund is success DC will get an intimation via Email.

EER
REFUND DETAILS

Details of EER Refund Details
Note: All fields are marked with * are mandatory

General Details	Description
PAT Cycle	PAT(2)/2016-2019
DC Registration Number	ALM00034KA
Designated Consumer Name	Balajisteel karnataka - TEST RECORD
Bank Account Name*	<input type="text" value="SREEDHAR"/>
Bank Name*	<input type="text" value="HDFCBANK"/>
Branch Address*	<input type="text" value="MARTHAHALLI"/>
A/c No*	<input type="text" value="98788777777777"/>
Account Type*	<input type="text" value="Current"/>

Figure 158: EE Registration –Refund Details

12.6.Approved Eligible Entity Registration

On the successful registration of Eligible Entity Registration the application will be submitted to Registry for further verification and approval.

Once the Registry Approve the application DC can see the status as approved in PAT Net portal. Once the application approved DC can download EER Certificate as shown below.

Eligible Entity Registration					
Form				Status	
Edit Info	Submit Transaction Details			Approved	

Partial Participation Details			Download			
Form	Status	Certificate	Invoice	Advance Receipt	Refund Voucher	
View	Verified					

Figure 159: EE Registration –Approved application by Registry

12.7.Partial ESCerts Introduction

Partials ESCerts Introduction is the feature available for the DC who have valid ESCerts in hand. In case DC don't want to introduce all the ESCerts at a time by paying the ESCerts Fee, can pay only few ESCerts at the time of Registration. The number of ESCerts DC want to introduce need to mention at the time of registration in the Payment Section as shown below. So DC need to pay only for those many ESCerts. On verification of this payment this ESCerts will get added to the trading account of DC.

Registration Info

General Details	Description
One Time Registration Fee	0
ESCCerts to be introduced for Trading	0
ESCCerts Fee	39000
Total Fee: Basic Value	39000
TDS deducted by DC (%)	0
POSOCO's TDS share (50%)	0.00
BEE's TDS share (50%)	0.00
Total TDS deducted by DC	0.00

Figure 160: Partial ESCerts Introduction

Later if DC want to introduce some more ESCerts for trading then click on the Submit Transaction link available in the dashboard. All introduced ESCerts information also can see and the related Invoice can be downloaded as shown below.

Eligible Entry Registration		Download			
Form	Status	Certificate	Invoice	Advance Receipt	Refund Voucher
Edit Info	Submit Transaction Details				
Partial Participation Details					
Form	Status	Certificate	Invoice	Advance Receipt	Refund Voucher
View	Verified				
View	Verified				
View	Verified				

Figure 161: Partial ESCerts Introductions

13. Trading Dashboard

On Click of **MY DASHBOARD**, list of options will be available for the menu. On click of **Trading Dashboard**, it navigates to Trading Dashboard which contains Trading information of a participated PAT Cycle.





Figure 162: BEE PATNet Trading Dashboard

The Trading Dashboard includes 3 sections.

- a) ESCerts ISSUED\ENTITLED TO BE PURCHASED
- b) Trading
- c) BANKED/EXTINGUISHED ESCERTS

13.1. ESCerts ISSUED\ENTITLED TO BE PURCHASED

On approval of E-filing by the Ministry of Power (MoP) “ESCerts ISSUED\ENTITLED TO BE PURCHASED “information will show for the corresponding PATCYCLES.



PAT Cycle	ESCerts Claimed	ESCerts Issued	Entitled to be Purchased	Eligibility Type	Sr.No. From	Sr.No. To
PAT(1)2012-2015	3100	3100	0	Seller	01-05907256-DIS00361KA-110521	01-05910355-DIS00361KA-110521

Figure 163: ESCerts ISSUED\ENTITLED TO BE PURCHASED

13.2. Trading

In this section, trading information of different Trading PAT Cycles is included. On click of Trading PAT Cycle, it displays the list of ESCerts sold or purchased in different Exchanges (IEX/PXIL).

TRADING

PAT(1)2012-2015 PAT(2)2016-2019

Banked ESCert: From Previous Cycle	Eligibility Type:	ESCerts Issued:	Opening Balance: (Banked ESCerts From Previous Cycle + ESCerts Issued)	Closing Balance:	Total Sold:
0	Seller	3100	3100	500	1900

Trading Date	Opening Balance	Closing Balance	No. of ESCerts Sold	Balance ESCerts Sr.No From - Sr.No To	Exchange	No. of ESCerts Traded
27-05-2021	2400	500	1900	01-05909156-DIS00361KA-110521 to 01-05907756-DIS00361KA-110521	IEX	1900

Total ESCerts Sold in IEX	1900
Total ESCerts Sold in PXIL	0
Grand Total	1900

Figure 164: Trading Section

If trading records are not available for corresponding Trading PAT Cycle, a message will appear “There is no Trading records available” as shown in below image.

TRADING

PAT(1)2012-2015 PAT(2)2016-2019

There is no trading records available.....!

Figure 165: Banked/Extinguished ESCerts section

13.3. Banked/Extinguished ESCerts

On approval of ESCerts Extinguishment by users of Power System Operation Corporation Limited – POSOCO, a view for “BANKED/EXTINGUISHED ESCERTS” will be presented for the corresponding PAT Cycle.

BANKED/EXTINGUISHED ESCERTS												
PAT Cycle	Eligibility	Opening Balance (Banked ESCert From Previous Cycle + ESCerts Issued)	Closing Balance	Total Sold	Entitle to be Purchased	Total to be Purchased (Entitled to be Purchased - Banked ESCert From Previous Cycle)	Total Purchased	Short Fall	Extinguished	Banked	Form D Submission Date	Compliance
PAT(1)2012-2015	Seller	3100	1200	1900	0	0	0	0	0	1200	10-05-2021	Yes

Figure 166: Banked/Extinguished ESCerts section

14. Submission of FORM D by Plant Head for Non-Eligibility Entity Registration

This section explains the process of filing Form D.

The DCs who were not part of Eligible Entity Registration (EER) process will be able to submit FORM D for a PAT Cycle.

3. Click the link (<https://escerts.gov.in>).
4. The ‘BEE PATNET Portal’ login page appears.
5. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
6. Click **My Dashboard** on the top left of the home page.



Figure 167: Click My Dashboard

7. The menus available under ‘MY Dashboard’ are presented. Click **Dashboard** menu from the list.




Figure 168: Click Dashboard Function

8. The 'DC Dashboard – PAT Cycles' page appears as shown in below image.
9. The PAT Cycle in which DC is currently participating will be highlighted as shown below.




Figure 169: Click Running PAT Cycle

10. Click on PAT Cycle image to open the respective PAT Cycle Dashboard.





Figure 170: DC DASHBOARD

11. Click on the Compliance tab to view Compliance data.




The screenshot shows the BEE dashboard for user Hamendra. The main heading is "DIS00165KA - ELECTRICITY DISCOM KARNATAKA RAMMURTHYNAGAR" with a sub-heading "PAT Cycle: PAT(2)2016-2019". Below this are five menu items: PAT Forms, ESCerts Issuance, Check Verification, Trading, and Compliance. A table below the menu items displays compliance data:

Form D	ESCerts Submitted For Compliance	Balance ESCerts [After Compliance]	Penalty[No. Of ESCerts]
Submit	0		

Figure 171: Compliance Information

10. Click on **Submit** link under 'Form D' field to enter Form D details.



This screenshot is similar to Figure 171 but highlights the "Submit" link under the "Form D" column of the table and the "Compliance" menu item above it.

Figure 172: Submit link

If Eligibility type for a DC for that PAT cycle is seller then following fields will be presented on Form-D:

Let's consider an example, in which DC was issued 345 ESCerts from MoP for that PAT Cycle.

1. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
2. Click on the PAT Cycle image to open that PAT Cycle Dashboard.
3. Click on the Compliance tab to view Compliance Data.
4. 'FORM D' page appears for a DC having Eligibility type as Seller as shown in the below image.

Compliance	Value	Info
Energy Saving Certificates	345	Issued by MoP
ESCerts Sold	0	ESCerts Sold
Banked ESCerts	0	NA
Balance Energy Saving Certificates	345	Validity till next PAT Cycle

I/We undertake that the information supplied in compliance with energy consumption and standard documents in this Form 'D' is accurate to the best of my/our knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/we agree to extend necessary assistance in case of any enquiry is made in the matter.

Cancel
Submit

Figure 173: FORM D page details for a seller

5. Energy saving certificates ISSUED by MOP is 345.
6. If DC has not sold any ESCerts, ESCerts sold value is zero.
7. There is no banked ESCerts for the DC
8. Balance Energy Saving Certificates (ESCerts) will be 345 and those will be marked as valid till next PAT Cycle. The balance no. of ESCerts will be same as the no. of issued ESCerts, since DC didn't sell any of the ESCerts and has Banked ESCerts values as zero.
9. Select the **Check box** to acknowledge the presented field information.
10. Click on **Submit** button to submit the form.

11. Below confirmation pop-up message is presented to proceed with Form D submission, click **OK**.





Figure 174: Proceed Message

12. On click of OK, a confirmation message 'Form has been Generated Successfully' is presented as shown below.



FORM-D

Form has been generated successfully!

Guidelines

Compliance of Energy Consumption Norms and Standard Document

General Info	Details
Name of Designated Consumer	ELECTRICITY DISCOM KARNATAKA RAMMURTHYNAGAR
Registration Number	DIS00165KA
Sector	DISCOM
Sub Sector	DISCOM
Performance Assessment Document(Form 'A')	<input checked="" type="radio"/> Submitted <input type="radio"/> Not Submitted 02-06-2021

Figure 175: FORM D Success Page

If Eligibility type for a DC for that PAT cycle is buyer then following fields will be presented on Form-D:

Let's consider an example, in which DC was asked to purchase 345 ESCerts from MoP for that PAT Cycle.

1. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
2. Click on the PAT Cycle image to open that PAT Cycle Dashboard.
3. Click on the Compliance tab to view Compliance Data.
4. On Click of **Submit** link, under 'Form D' field to enter the Form D details. The 'FORM D' page appears as shown in the below image.

FORM-D
Compliance of Energy Consumption Norms and Standard Document
[Guidelines](#)

Compliance	Value	Info
Energy Saving Certificates	345	Entitled to be Purchased by MoP
Energy Saving Certificates submitted for Compliance	0	
ESCerts Purchased	0	ESCerts Purchased
Banked ESCerts	0	NA
ESCerts Blocked for Compliance	0	
Balance Energy Saving Certificates	345	Shortfall - Non Compliance

I/We undertake that the information supplied in compliance with energy consumption and standard documents in this Form 'D' is accurate to the best of my/our knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/we agree to extend necessary assistance in case of any enquiry is made in the matter.

Cancel
Submit

FORM 176: FORM D page details for a buyer

5. Energy saving certificates entitled to be purchased by MoP is 345.
6. DC has not purchased any ESCerts, ESCerts Purchased value is zero.
7. There is no Energy saving Certificates submitted for Compliance for the DC.
8. There is no Banked ESCerts for that DC.
9. There is no ESCerts Banked for Compliance for that DC.
10. Balance Energy Saving Certificates will be 345 and will be marked as Shortfall – Non Compliance as DC has not purchased any ESCerts for that PAT cycle and did not meet the compliance.
11. Select the **Check box** to acknowledge the presented field information.
12. Click on **Submit** button to submit the form.
13. The confirmation pop-up message to proceed Form D submission appears, click **Ok**.




Figure 177: Proceed Message

14. On click of OK, a confirmation message - 'Form has been Generated Successfully' is presented as shown below.




Figure 178: FORM D Success Page

15. Submission of FORM D by Plant Head for a DC who has participated in Eligibility Entity Registration Process

This section explains the process of filing Form D.

The DCs who were part of Eligible Entity Registration (EER) process will be able to submit FORM D for that PAT Cycle.

1. Click the link (<https://escerts.gov.in>).
2. The 'BEE PATNET Portal' login page appears.
3. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears and is shown below.
4. Click My Dashboard on the top left of the home page.



Figure 179: Click My Dashboard

5. The menus available under 'MY Dashboard' are presented. Click **Dashboard** menu from the list.




Figure 180: Click Dashboard Function

6. The 'DC Dashboard – PAT Cycles' page appears.
7. The PAT Cycle in which DC is currently participating will be highlighted as shown below.




Figure 181: Click Running PAT Cycle

8. Click on the PAT Cycle image to open the respective PAT Cycle Dashboard.




Figure 182: DC information page

9. Click on the Compliance tab to view Compliance data.




Figure 183: Compliance information page

10. Click on **Submit** link under 'Form D' field to enter Form D details.




Figure 184: Submit Link

If Eligibility type for a DC for that PAT cycle is seller then following fields will be presented on Form-D:

Let's consider an example, in which DC was issued 567 ESCerts from MoP for that PAT Cycle and sold 400 ESCerts during trading sessions.

1. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
2. Click on the PAT Cycle image to open that PAT Cycle Dashboard.
3. Click on the Compliance tab to view Compliance data.
4. 'FORM D' page appears for a DC having Eligibility type as Seller as shown in the below image.




Figure 185: FORM D Page Details for a Seller

5. Energy saving certificates ISSUED by MOP is 567
6. DC has sold 400 ESCerts
7. There is no banked ESCerts for that DC
8. Balance Energy Saving Certificates (ESCerts) will be 167 and those will be marked as valid till next PAT Cycle..
9. Select the **Check box** to acknowledge the presented field information.
10. Click **Submit** to submit the form.
11. Below confirmation pop-up message is presented to proceed with Form D submission, click **OK**.



Figure 186: Proceed Message

12. On click of OK, a confirmation message 'Form has been Generated Successfully' is presented as shown below





Figure 187: FORM D Success Page

If Eligibility type for a DC for that PAT cycle is buyer then following fields will be presented on Form-D:

Let's consider an example, in which DC was asked to purchase 1900 ESCerts from MoP for a PAT Cycle and DC has purchased 1200 ESCerts during Trading sessions.

1. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
2. Click on the PAT Cycle image to open the respective PAT Cycle Dashboard.
3. Click on the Compliance tab to view Compliance data.
4. 'FORM D' page appears for a DC having Eligibility type as Buyer as shown in below image.



Compliance	Value	Info
Energy Saving Certificates	1900	Entitled to be Purchased by MoP
Energy Saving Certificates submitted for Compliance	1200	
ESCerts Purchased	1200	ESCerts Purchased
Banked ESCerts	0	NA
ESCerts Blocked for Compliance	0	
Balance Energy Saving Certificates	700	Short fall - Non-compliance

I/We undertake that the information supplied in compliance with energy consumption and standard documents in this Form 'D' is accurate to the best of my/our knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/we agree to extend necessary assistance in case of any enquiry is made in the matter.

Cancel Submit

Figure 188: FORM D Details Page

5. Energy saving certificates entitled to be purchased by MOP is 1900.
6. DC has Purchased 1200 ESCerts
7. Energy saving certificates submitted for compliance 1200
8. There is no banked ESCerts for the DC
9. There is no ESCerts Blocked for Compliance for the DC
10. Balance Energy Saving Certificates (ESCerts) will be 700 and marked as Shortfall – Non Compliance. Though DC has purchased ESCerts during trading for that PAT cycle but did not meet compliance
11. Select the **Check box** to acknowledge the presented field information.
12. Click **Submit** to submit the form.
13. The confirmation message is presented to proceed with Form D submission, click **OK**.




Figure 189: Proceed Message

14. On click of OK, a confirmation message, 'Form has been Generated Successfully' is presented as shown below.




Figure 190: FORM D Success Page

Let's consider another example, in which DC was asked to purchase 225 ESCerts from MoP for a PAT Cycle , however, DC has purchased 625 ESCerts during Trading sessions i.e. 400 ESCerts more (extra bought)

1. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
2. Click on the PAT Cycle image to open that PAT Cycle Dashboard.
3. Click on the Compliance tab to view Compliance data.
4. 'FORM D' page appears for a DC having Eligibility type as Buyer and who bought extra ESCerts as shown in below image.

FORM-D
Compliance of Energy Consumption Norms and Standard Document
[Guidelines](#)

Compliance	Value	Info
Energy Saving Certificates	225	Entitled to be Purchased by MoP
Energy Saving Certificates submitted for Compliance	225	
ESCerts Purchased	625	ESCerts Purchased
Banked ESCerts	0	NA
ESCerts Blocked for Compliance	0	
Balance Energy Saving Certificates	400	Extra Bought - For compliance purpose only Validity till next PAT Cycle

We undertake that the information supplied in compliance with energy consumption and standard documents in this Form 'D' is accurate to the best of my/our knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/we agree to extend necessary assistance in case of any enquiry is made in the matter.

Cancel
Submit

Figure 191: FORM D Details Page

5. Energy saving certificates (ESCerts) entitled to be purchased by MOP is 225.
6. DC has Purchased 625 ESCerts
7. Energy saving certificates submitted for compliance 225
8. There is no banked ESCerts for the DC
9. There is no ESCerts Blocked for Compliance for the DC
10. Balance Energy Saving Certificates (ESCerts) will be 400 and marked as Extra Bought –Compliance Purpose Only. This means the extra bought ESCerts can be utilized only for compliance (can not be sold) and are valid till next PAT Cycle.
11. Select the **Check box** to acknowledge the presented information.
12. Click **Submit** to submit the form.
13. The confirmation message is presented to proceed with Form D submission, click **OK**.


patnet.positiveedge.net:447 says

Are you sure want to proceed?

OK
Cancel

Figure 192: Proceed Message

14. On click of OK, a confirmation message, 'Form has been Generated Successfully' is presented as shown below.



Form has been generated successfully!


Compliance of Energy Consumption Norms and Standard Document

General Info	Details
Name of Designated Consumer	ELECTRICITY DISCOM KARNATAKA MYSORE
Registration Number	DIS00166KA
Sector	DISCOM
Sub Sector	DISCOM
Performance Assessment Document(Form 'A')	<input checked="" type="radio"/> Submitted <input type="radio"/> Not Submitted 02-06-2021

Figure 193: FORM D Success Page

Let's consider another example, in which DC was issued 1000 ESCerts from MoP for a PAT Cycle and DC has 1200 Banked ESCerts from previous PAT cycle.

1. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
2. Click on the PAT Cycle image to open that PAT Cycle Dashboard.
3. Click on the Compliance tab to view Compliance Data.
4. 'FORM D' page appears for a DC having Eligibility type as Seller as shown in below image.



Compliance of Energy Consumption Norms and Standard Document

Sub Sector: DISCOM

Performance Assessment Document(Form 'A'): Submitted Not Submitted 28-05-2021

Compliance	Value	Info
Energy Saving Certificates	1000	Issued by MoP
ESCerts Sold	0	ESCerts Sold
Banked ESCerts(from PAT(1)2012-2015)	1200	Compliance + Sell Validity till current PAT Cycle
Balance Energy Saving Certificates	2200	1200 - Validity till current PAT Cycle 1000 - Validity till next PAT Cycle

I/We undertake that the information supplied in compliance with energy consumption and standard documents in this Form 'D' is accurate to the best of my/our knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/we agree to extend necessary assistance in case of any enquiry is made in the matter.

Cancel Submit

Figure 194: FORM D Details Page

5. Energy saving certificates ISSUED by MOP is 1000.
6. DC has not sold any ESCerts during the trading sessions
7. The no. of banked ESCerts from earlier PAT cycle for that DC is 1200 and those are valid in current PAT Cycle only.

8. Balance Energy Saving Certificates (ESCerts) will be 2200. In this value of 2200, 1000 ESCerts issued as part of this PAT cycle are valid till next PAT CYCLE and 1200 Banked ESCerts from previous PAT cycle are valid in current PAT cycle only.
9. Select the **Check box** to acknowledge the presented information.
10. Click **Submit** to submit the form.
11. The confirmation message is presented to proceed with Form D submission, click **OK**.





Figure 195: Proceed Message

12. On click of OK, a confirmation message, 'Form has been Generated Successfully' is presented as shown below



FORM-D Guidelines

Form has been generated successfully!

Compliance of Energy Consumption Norms and Standard Document

Registration Number: DIS00361KA

Sector: DISCOM

Sub Sector: DISCOM


Performance Assessment Document(Form 'A'): Submitted Not Submitted 28-05-2021

Compliance	Value	Info
Energy Saving Certificates	1000	Issued by MoP
ESCerts Sold	0	ESCerts Sold
Banked ESCerts(from PAT(1)2012-2015)	1200	Compliance + Sell Validity till current PAT Cycle
Balance Energy Saving Certificates	2200	1200 – Validity till current PAT Cycle 1000 – Validity till next PAT Cycle

Figure 196: FORM D Success Page

Let's consider another example, in which DC was asked to purchase 200 ESCerts from MoP for a PAT Cycle whereas DC was having 2700 Banked ESCerts from previous PAT cycle where the DC was Seller.

1. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
2. Click on the PAT Cycle image to open that PAT Cycle Dashboard.
3. Click on the Compliance tab to view Compliance data.
4. 'FORM D' page appears for a DC having Eligibility type as Buyer but in a way the DC becomes Seller owing to banked ESCerts as shown in below image



FORM-D Compliance of Energy Consumption Norms and Standard Document Guidelines

Compliance	Value	Info
Energy Saving Certificates	200	Entitled to be Purchased by MoP
Energy Saving Certificates submitted for Compliance	200	
ESCerts Sold	2400	ESCerts Sold
Banked ESCerts(from PAT(1)2012-2015)	2700	Compliance - Sell Validity till current PAT Cycle
ESCerts Blocked for Compliance	200	
Balance Energy Saving Certificates	100	Validity till current PAT Cycle

I/We undertake that the information supplied in compliance with energy consumption and standard documents in this Form 'D' is accurate to the best of my/our knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/we agree to extend necessary assistance in case of any enquiry is made in the matter.

Cancel Submit

Figure 197: FORM D Page Details

5. Energy saving certificates entitled to be purchased by MOP is 200.
6. Energy Saving Certificates submitted for Compliance is 200.
7. DC has sold 2400 ESCerts from Banked ESCerts.
8. Banked ESCerts for the DC is 2700 and validity till current PAT CYCLE only.
9. The ESCerts Blocked for Compliance 200
10. Balance Energy Saving Certificates will be 100. In this 100 ESCerts validity will be till next PAT CYCLE.
11. Select the **Check box** to acknowledge the presented information.
12. Click **Submit** to submit the form.
13. The confirmation message is presented to proceed with Form D submission, click **OK**.




Figure 198: Proceed Message

14. On click of OK, a confirmation message - 'Form has been Generated Successfully' is presented as shown below




Figure 199: FORM D Success Page

Let's consider another example, in which DC was issued 300 ESCerts from MoP for a PAT Cycle whereas DC is having 2800 Banked ESCerts from previous PAT cycle where he was Seller

1. On Successful login to the BEE PATNET portal with Plant Head user name and password, the DC Home page appears.
2. Click on the PAT Cycle image to open that PAT Cycle Dashboard.
3. Click on the Compliance tab to view Compliance data.
4. 'FORM D' page for a DC having Eligibility type as Seller having banked ESCerts from previous PAT cycle is shown in below image.

Compliance	Value	Info
Energy Saving Certificates	300	Issued by MoP
ESCerts Sold	1100	ESCerts Sold
Banked ESCerts(from PAT(1)2012-2015)	2800	Compliance + Sell Validity till current PAT Cycle
Balance Energy Saving Certificates	2000	1700 - Validity till current PAT Cycle 300 - Validity till next PAT Cycle

/We undertake that the information supplied in compliance with energy consumption and standard documents in this Form 'D' is accurate to the best of my/our knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/we agree to extend necessary assistance in case of any enquiry is made in the matter.

Cancel
Submit

Figure 200: FORM D Details Page

5. Energy Saving certificates Issued by MOP is 300.
6. DC has sold 1100 ESCerts from Banked ESCerts during the trading sessions.
7. Banked ESCerts for the DC is 2800 that are carried forward from previous PAT cycle for which validity is till current PAT CYCLE.
8. Balance Energy Saving Certificates will be 2000. In this value of 2000, there are 1700 ESCerts which are valid till Current PAT cycle and 300 ESCerts that will be valid till Next PAT cycle.
9. Select the **Check box** to acknowledge the entered field information.
10. Click **Submit** to submit the form.
11. The confirmation message is presented to proceed with Form D submission, click **OK**.

patnet.positiveedge.net:447 says

Are you sure want to proceed?

OK
Cancel

Figure 201: Proceed Message

12. On click of OK, a confirmation message - 'Form has been Generated Successfully' is presented as shown below.

FORM-D
Form has been generated successfully!
Guidelines

Compliance of Energy Consumption Norms and Standard Document

Sub Sector: DISCOM

Performance Assessment Document(Form 'A'): Submitted Not Submitted | 28-05-2021

Compliance	Value	Info
Energy Saving Certificates	300	Issued by MoP
ESCerts Sold	1100	ESCerts Sold
Banked ESCerts(from PAT(1)2012-2015)	2800	Compliance + Sell Validity till current PAT Cycle
Balance Energy Saving Certificates	2000	1700 – Validity till current PAT Cycle 300 – Validity till next PAT Cycle

I/We undertake that the information supplied in compliance with energy consumption and standard documents in this Form 'D' is accurate to the best of my/our knowledge and if any of the information supplied is found to be incorrect and such information result into loss to the Central Government or State Government or any of the authority under them or any other person affected, I/we undertake to indemnify such loss. I/we agree to extend necessary assistance in case of any enquiry is made in the matter.

Figure 202: FORM D Success Message